



**Language file description file for
- DBC44x (Mitel 7444/7446),
- DBC43x (Mitel 7433/7434)**

NOTICE

The information contained in this document is believed to be accurate in all respects but is not warranted by Mitel Networks™ Corporation (MITEL®). Mitel makes no warranty of any kind with regards to this material, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose.

The information is subject to change without notice and should not be construed in any way as a commitment by Mitel or any of its affiliates or subsidiaries. Mitel and its affiliates and subsidiaries assume no responsibility for any errors or omissions in this document. Revisions of this document or new editions of it may be issued to incorporate such changes.

No part of this document can be reproduced or transmitted in any form or by any means - electronic or mechanical - for any purpose without written permission from Mitel Networks Corporation.

Trademarks

Mitel® is a registered trademark of Mitel Networks Corporation.

All trademarks mentioned in this document are the property of their respective owners, including Mitel Networks Corporation. All rights reserved.

®, TM Trademark of Mitel Networks Corporation

©Copyright 2015, Mitel Networks Corporation

All rights reserved

Doc Number: 1551-CAA 158 0059

Revision: G



1 Introduction

- 1.1 Abstract
- 1.2 References
- 1.3 Acronyms and Abbreviations

2 Description

- 2.1 File syntax
- 2.2 Change of a text string shown in det display
- 2.3 [LANGUAGE]
- 2.4 [LANGUAGE NAMES]
- 2.5 [MONTH NAMES]
- 2.6 [WEEK DAYS]
- 2.7 [TIME NAMES]
- 2.8 [MENU TEXTS]
- 2.9 [MAIN TEXTS]
- 2.10 [WEBB TEXTS]
- 2.11 [INPUT LANGUAGE]
- 2.12 [UPPER_CASE]
- 2.13 [LOWER_CASE]



[1] Introduction

1.1 Abstract

The aim of this document is to describe the format of the language file containing language dependant texts and characters that are used for the DBC 43x 01 and DBC 44x 01.

Note that some texts may be sent from the PBX.

This document is intended for system administrators that want to change text strings shown in the telephone display, but also for translators making localization of files.

1.2 References

Some parameters concerning language settings need to be set in the configuration file, see description for CONFIGURATION FILE FOR DBC 43x and DBC 44x.

1.3 Acronyms and Abbreviations

The following acronyms and abbreviations are used in the text:

DHCP - Dynamic Host Configuration Protocol

DNS - Domain Name System

GK - GateKeeper

HTTP - Hyper Text Transfer Protocol

LAN - Local Area Network

Reg. - Regular (Not Italic or Bold text)



2 Description

The string table in the tab *2.B Description* contains the following columns:

<i>column name</i>	<i>definition</i>
string type	see section 2.1 File Syntax
string ID	The identity of the text string (used for localization)
default value	The English text
use	Describes in which context the text is used
pixel check	The text string must be checked according to the maximum pixel length. Can have the values for DBC 43x, DBC444 and DBC446.
language file	States in which language file the text string shall be included. Values can be DBC 43x, DBC444, DBC446, or two of them or all.
display rows	States the maximum rows in which the text string can be displayed
font size	The size of the text. Reg. = Regular, Cond. = Condensed.
max. length	The recommended maximum length in number of characters that the translated text can have.
max. pixel length	The number of characters is dependant on how many pixels a character consists of.
not to be translated	The maximum length in number of pixels that the translated text can have. If the text string can be displayed in multiple rows, it is the maximum length in number of pixels that the translated text can have in each row.

2.1 File syntax

The file contains all languages supported by the DBC 43x 01 and DBC 44x 01.

The file should be stored in the directory defined in the Config file, usually /dbc43x 01 or /dbc44x 01 directory of the HTTP server.

There is one language file for each of the following types of phones, DBC43x, DBC444 and DBC446.

The file should be saved in 16 bit UNICODE file format, this can be done in Microsoft Word.

The file consists of the following string types and the syntax should be as follows:

```
[LANGUAGE]
[LANGUAGE_NAMES]
[MONTH_NAMES]
[WEEK_DAYS]
[TIME_NAMES]
[MENU_TEXTS]
```

[MAIN_TEXTS]
[WEBB_TEXTS]
[INPUT_LANGUAGE]
[UPPER_CASE]
[LOWER_CASE]
[END]

2.2 Change of a text string shown in the display

Sometimes there is a need to change a text string shown in the display in the telephone.

An example is when the used word for an absence reason, in the My Presence menu, shall be adapted to what is used in the PBX.

The system administrator can change the text string in the following way:

1. Use Microsoft Word to edit the language file.
2. Find the word to edit. If it is an absence reason word, word T155-T168/T155b-T168b/T155c-T168c
3. Edit the word in the specific language that shall be changed.
4. Store the edited language file on the software server.

Use a different revision in the file name; if the original file was called d44x01-lang_R1A.txt call the edited file d44x01-lang_R1A1.txt

5. Change the revision of the language file in the configuration file.
6. Reboot the telephone, either by command from the gatekeeper or manually.

Note! No text string can be removed or added. The only modification that is working is to change an existing text string.

2.2.1 Forced wrap around to the next line

It is possible to force a wrap around to the next line by writing \n in the text string in the language file.

Example: Your connection to \nthe world. Will be shown in the display as:

**Your connection to
the world**

It is also possible to conditionally force a word wrap around, after hyphen, by writing \- in the word in the language file. This can be useful for shortcut keys.

The word is written on one line without a hyphen if there is room enough on one line.

The word is written on two lines with a hyphen if:

1. the definition for the text string allows that the text string can be on two rows, see section 2.B below where the column **display rows** shows if the text string can be wrapped to two lines
2. if there is not space enough on one line

Example: The text string with string id T360b *Free on busy*. The translated Swedish text string *Ledig annan linje*, will be shown in the shortcut key label in the display ↴

**Ledig an-
nan linje**

In the menu **Availability** the same string will be shown as:

Ledig annan linje:

because there is space enough on one line.

2.3 [LANGUAGE]

Language data such as two letter abbreviation for the available languages, revision, date and document number.

2.4 [LANGUAGE NAMES]

Names of the available languages.

2.5 [MONTH NAMES]

Three letter abbreviation of months.

2.6 [WEEK DAYS]

Two letter abbreviation of week days starting from Sunday.

2.7 [TIME NAMES]

One letter abbreviation of time names: Year, Month, Day, Hour and Minute.

2.8 [MENU TEXTS]

Menu texts or soft-key text strings is the texts above the soft-keys and in the top menu bar.
The text is automatically centred over each soft-key by the application.

2.9 [MAIN TEXTS]

This section describes the words that can be up to 40 characters wide.

Note! If the same string appears in both DBC 44x and DBC 43x, they have unique entries in the table.

2.10 [WEBB_TEXTS]

Text strings used by WEB browser at an authentication dialog with an internet server.

2.11 [INPUT_LANGUAGE]

The input language specifies the names of the alternative keypad character set used for entering e.g. names in the contacts.

2.12 [UPPER_CASE]

Upper case keypad characters for the different input languages.

2.13 [LOWER_CASE]

Lower case keypad characters for the different input languages.

2.14 [END]



Language file for DBC 43x, 444, 446

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[LANGUAGE_NAMES]										
[LANGUAGE_NAMES]	A001	English	Name of the language.	DBC446	DBC446	1	14 Reg.	25	400	
[LANGUAGE_NAMES]	A001b	English	Name of the language.	DBC43x	DBC43x	1	8 Reg	25	120	
[LANGUAGE_NAMES]	A001c	English	Name of the language.	DBC444	DBC444	1	16 Bold	25	275	
[MONTH_NAMES]										
[MONTH_NAMES]	A002	Jan	January.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A003	Feb	February.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A004	Mar	March.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A005	Apr	April.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A006	May	May.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A007	Jun	Jun.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A008	Jul	July.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A009	Aug	August.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A010	Sep	September.		DBC446, DBC43x, DBC444	1		3		

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MONTH_NAMES]	A011	Oct	October.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A012	Nov	November.		DBC446, DBC43x, DBC444	1		3		
[MONTH_NAMES]	A013	Dec	December.		DBC446, DBC43x, DBC444	1		3		
[WEEK_DAYS]										
[WEEK_DAYS]	A014	Su	Sunday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A015	Mo	Monday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A016	Tu	Tuesday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A017	We	Wednesday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A018	Th	Thursday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A019	Fr	Friday.		DBC446, DBC43x, DBC444	1		2		
[WEEK_DAYS]	A020	Sa	Saturday.		DBC446, DBC43x, DBC444	1		2		
[TIME_NAMES]										
[TIME_NAMES]	A021	Y	Year.		DBC446, DBC43x, DBC444	1		1		
[TIME_NAMES]	A022	M	Month.		DBC446, DBC43x, DBC444	1		1		
[TIME_NAMES]	A023	D	Day.		DBC446, DBC43x, DBC444	1		1		
[TIME_NAMES]	A024	H	Hour.		DBC446, DBC43x, DBC444	1		1		
[TIME_NAMES]	A025	M	Minute.		DBC446, DBC43x, DBC444	1		1		
[MENU_TEXTS]										

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M001		Blank. Used for not showing menu choice.							TRUE
[MENU_TEXTS]	M002	Settings	Modify property (data) settings.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M002b	Settings	Modify property (data) settings.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M002c	Settings	Modify property (data) settings.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M003	Contacts	Used for searching for telephone numbers by name.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M003b	Contacts	Used for searching for telephone numbers by name.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M004	CallList	Look at the call history list.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M004b	CallList	Look at the call history list.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M005	Erase	Remove last character from display.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M005b	Erase	Remove last character from display.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M005c	Erase	Remove last character from display.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M006	Call	Start outgoing call. Used in Enbloc mode.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M006b	Call	Start outgoing call. Used in Enbloc mode.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M006c	Call	Start outgoing call. Used in Enbloc mode.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M007	Reject	Do not answer incoming call.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M007b	Reject	Do not answer incoming call.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M007c	Reject	Do not answer incoming call.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M008	Hold	Put call on hold.	DBC446	DBC446	1	14 Bold	15	92	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M008b	Hold	Put call on hold.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M008c	Hold	Put call on hold.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M010	Exit	Leave menu.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M010b	Exit	Leave menu.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M010c	Exit	Leave menu.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M011	Delete	Remove item in list.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M011b	Delete	Remove item in list.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M011c	Delete	Remove item in list.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M012	Edit	Change property of item.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M012b	Edit	Change property of item.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M012c	Edit	Change property of item.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M013	more...	Move to more menu choices on same level.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M013b	more...	Move to more menu choices on same level.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M013c	more...	Move to more menu choices on same level.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M014	Yes	Positive answer.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M014b	Yes	Positive answer.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M014c	Yes	Positive answer.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M015	No	Negative answer.	DBC446	DBC446	1	14 Bold	15	92	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M015b	No	Negative answer.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M015c	No	Negative answer.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M018	Select	Select item in a list.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M018b	Select	Select item in a list.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M018c	Select	Select item in a list.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M019	Log on	Log on to the system (gatekeeper).	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M019b	Log on	Log on to the system (gatekeeper).	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M019c	Log on	Log on to the system (gatekeeper).	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M020	Log off	Log off from the system (gatekeeper).	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M020b	Log off	Log off from the system (gatekeeper).	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M021	Cancel	Leave menu without saving change.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M021b	Cancel	Leave menu without saving change.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M021c	Cancel	Leave menu without saving change.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M022	Save	Save setting.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M022b	Save	Save setting.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M022c	Save	Save setting.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M023	Change	Change setting. Toggling between modes.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M023b	Change	Change setting. Toggling between modes.	DBC43x	DBC43x	1	8 Bold	15	62	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M023c	Change	Change setting. Toggling between modes.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M024	Back	Move back to previous menu choices on same level.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M024b	Back	Move back to previous menu choices on same level.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M024c	Back	Move back to previous menu choices on same level.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M025	AddContact	Add to contacts.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M025b	AddContact	Add to contacts.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M026	** Missed	Number of missed calls in the call history list. ** is locally replaced by the number of missed calls and can be anywhere in the text.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M026b	** Missed	Number of missed calls in the call history list. ** is locally replaced by the number of missed calls and can be anywhere in the text.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M027	Name	Edit name incontacts.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M027b	Name	Edit name incontacts.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M028	Number	Edit number incontacts.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M028b	Number	Edit number incontacts.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M029	OK	Answer ok on question.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M029b	OK	Answer ok on question.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M029c	OK	Answer ok on question.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M030	Search	Search in contacts.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M030b	Search	Search in contacts.	DBC43x	DBC43x	1	8 Bold	15	62	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M030c	Search	Search in contacts.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M031	Web	Browse on the Web.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M031b	Web	Browse on the Web.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M034	No Profile	Deactivate profile.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M034b	No Profile	Deactivate profile.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M034c	No Profile	Deactivate profile.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M036	Stop	Stop.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M036b	Stop	Stop.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M036c	Stop	Stop.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M038	CorpDirectory	Browse to external Corporate directory.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M038b	CorpDirectory	Browse to external Corporate directory.	DBC43x	DBC43x, DBC444	1	8 Bold	15	62	
[MENU_TEXTS]	M039	Retry	Press to retry.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M039b	Retry	Press to retry.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M039c	Retry	Press to retry.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M043	Messages	Show messages menu.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M043b	Messages	Show messages menu.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M043c	Messages	Show messages menu.	DBC444	DBC444	1	14 Bold,	15	138	
[MENU_TEXTS]	M044	Answer	Answer incoming call.	DBC446	DBC446	1	14 Bold	15	92	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M044b	Answer	Answer incoming call.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M044c	Answer	Answer incoming call.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M046	Close	Close the "more..." menu.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M046b	Close	Close the "more..." menu.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M046c	Close	Close the "more..." menu.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M047	Set	Set the setting.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M047b	Set	Set the setting.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M047c	Set	Set the setting.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M048	Done	Finalize the setting process.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M048b	Done	Finalize the setting process.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M048c	Done	Finalize the setting process.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M049	Add	Add one more entry.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M049b	Add	Add one more entry.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M049c	Add	Add one more entry.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M051	Clear	Clear one digit from the back of string.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M051b	Clear	Clear one digit from the back of string.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M051c	Clear	Clear one digit from the back of string.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M052	Operator	Shortcut to the operator	DBC43x	DBC43x	1	8 Bold	15	62	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M052b	Operator	Shortcut to the operator	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M052c	Operator	Shortcut to the operator	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M053	Callback	Callback from this soft key.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M053b	Callback	Callback from this soft key.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M053c	Callback	Callback from this soft key.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M054	Abort	Abort an action	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M054b	Abort	Abort an action	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M054c	Abort	Abort an action	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M055	EraseAll	Erase all digits in a String.	DBC444	DBC43x, DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M055b	EraseAll	Erase all digits in a String.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M056	Play	Play a ring signal or a melody.	DBC444	DBC43x, DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M056b	Play	Play a ring signal or a melody.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M057	Availability	My Presence, Follow-me, My profile, etc.	DBC444	DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M057b	Availability	My Presence, Follow-me, My profile, etc.	DBC43x	DBC43x	1	8 Bold	15	62	
[MENU_TEXTS]	M057c	Availability	My Presence, Follow-me, My profile, etc.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M058	Previous	Go to previous shortcut page.	DBC444	DBC43x, DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M058b	Previous	Go to previous shortcut page.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M059	Next	Go to next shortcut page.	DBC444	DBC43x, DBC444	1	14 Bold, Cond.	15	79	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
[MENU_TEXTS]	M059b	Next	Go to next shortcut page.	DBC446	DBC446	1	14 Bold	15	92	
[MENU_TEXTS]	M060	Details	To view the item details.	DBC444	DBC43x, DBC444	1	14 Bold, Cond.	15	79	
[MENU_TEXTS]	M060b	Details	To view the item details.	DBC446	DBC446	1	14 Bold	15	92	
MAIN_TEXTS										
MAIN_TEXTS	T001	Self test OK	Internal test mode.	DBC446	DBC446	1	18 Reg.	30	466	
MAIN_TEXTS	T001b	Self test OK	Internal test mode.	DBC43x	DBC43x	1	8 bold	30	128	
MAIN_TEXTS	T001c	Self test OK	Internal test mode.	DBC444	DBC444	1	16 bold	30	296	
MAIN_TEXTS	T002	Programmable Keys	Keys that can be programmed for numbers and procedures.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	25	468	
MAIN_TEXTS	T004	Current number:	Current number on programmable key	DBC446	DBC446	1	18Reg.	25	220	
MAIN_TEXTS	T004b	Current number:	Current number on programmable key	DBC43x	DBC43x, DBC444	1	8 Reg.	25	64	
MAIN_TEXTS	T007	Ring Character	Select ring character.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T007b	Ring Character	Select ring character.	DBC43x	DBC43x, DBC444 DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T008	Current ring character:	Current ring character.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	40	220	
MAIN_TEXTS	T009	Current ring character:	Current ring character.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T010	New character(0-9):	Enter new character.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	40	220	
MAIN_TEXTS	T011	New character(0-9):	Enter new character.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	26	128	
MAIN_TEXTS	T012	Time & Date	Select time and date.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T012b	Time & Date	Select time and date.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T012c	Time & Date	Select time and date.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T013	Time Format	Select time format.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T013b	Time Format	Select time format.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T013c	Time Format	Select time format.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T014	Date Format	Select date format.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T014b	Date Format	Select date format.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T014c	Date Format	Select date format.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T015	hour	12/24 hour format.	DBC446	DBC446	1	14 Reg.	20	80	
MAIN_TEXTS	T015b	hour	12/24 hour format.	DBC43x	DBC43x	1	8 Reg.	20	80	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T015c	hour	12/24 hour format.	DBC444	DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T016	Time	Set new time.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T016b	Time	Set new time.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T016c	Time	Set new time.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T017	Date	Set new date.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T017b	Date	Set new date.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T017c	Date	Set new date.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T018	Language	Select language used in menus etc.	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T018b	Language	Select language used in menus etc.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T018c	Language	Select language used in menus etc.	DBC444	DBC444	1	16 Bold	25	148	
MAIN_TEXTS	T019	Language not available!	Selected language is not available.	DBC446	DBC446, DBC43x	1	18 Reg.	40	480	
MAIN_TEXTS	T019b	Language not available!	Selected language is not available.	DBC444	DBC444	3	16 Bold	40	253	
MAIN_TEXTS	T020	Language not available!	Selected language is not available.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T021	Hearing Level	Select hearing level.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T021b	Hearing Level	Select hearing level.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T022	Standard	Standard hearing level.	DBC446	DBC446	1	18 FReg.	25	400	
MAIN_TEXTS	T022b	Standard	Standard hearing level.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	60	
MAIN_TEXTS	T023	Increased	Increased hearing level.	DBC446	DBC446	1	18 Reg.	25	400	
MAIN_TEXTS	T023b	Increased	Increased hearing level.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	60	
MAIN_TEXTS	T024	Network	LAN parameters e.g. IPaddress.	DBC446	DBC446	1	18 Reg.	25	468	
MAIN_TEXTS	T024b	Network	LAN parameters e.g. IPaddress.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T024c	Network	LAN parameters e.g. IPaddress.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T025	DHCP	Dynamic Host Configuration Protocol.	DBC446	DBC446	1	18 Reg.	20	300	
MAIN_TEXTS	T025b	DHCP	Dynamic Host Configuration Protocol.	DBC43x	DBC43x	1	8 Reg.	20	90	
MAIN_TEXTS	T025c	DHCP	Dynamic Host Configuration Protocol.	DBC444	DBC444	1	16 Bold	20	218	
MAIN_TEXTS	T028	Yes	Positive answer.	DBC446	DBC446	1	14 Reg.	10	70	
MAIN_TEXTS	T028b	Yes	Positive answer.	DBC43x	DBC43x	1	8 Reg.	10	30	
MAIN_TEXTS	T028c	Yes	Positive answer.	DBC444	DBC444	1	16 Bold	10	60	
MAIN_TEXTS	T029	No	Negative answer.	DBC446	DBC446	1	14 Reg.	10	70	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T029b	No	Negative answer.	DBC43x	DBC43x	1	8 Reg.	10	30	
MAIN_TEXTS	T029c	No	Negative answer.	DBC44	DBC44	1	16 Bold	10	60	
MAIN_TEXTS	T030	Default	Default setting.	DBC446	DBC446	1	18 Reg.	10	100	
MAIN_TEXTS	T030b	Default	Default setting.	DBC43x	DBC43x	1	8 Reg.	10	70	
MAIN_TEXTS	T030c	Default	Default setting.	DBC44	DBC44	1	16 Bold	10	90	
MAIN_TEXTS	T031	Web address	DNS name.	DBC446	DBC446	1	18 Reg.	25	100	
MAIN_TEXTS	T031b	Web address	DNS name.	DBC43x	DBC43x	1	8 Reg.	25	100	
MAIN_TEXTS	T031c	Web address	DNS name.	DBC44	DBC44	1	16 Bold	25	270	
MAIN_TEXTS	T032	IP address	IP v.4 address.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T032b	IP address	IP v.4 address.	DBC44	DBC44	1	16 Bold	25	168	
MAIN_TEXTS	T033	IPadd	IP v.4 address.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	6	32	
MAIN_TEXTS	T034	Subnet Mask	Select subnet mask.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T034b	Subnet Mask	Select subnet mask.	DBC44	DBC44	1	16 Bold	25	168	
MAIN_TEXTS	T035	Mask	Select subnet mask.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	6	32	
MAIN_TEXTS	T036	Default Gateway	Select default gateway.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T036b	Default Gateway	Select default gateway.	DBC44	DBC44	1	16 Bold	25	168	
MAIN_TEXTS	T037	D GW	Select default gateway.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	6	32	
MAIN_TEXTS	T038	Automatic SW server	Short for ""Do you want to retrieve the IP address of the software server automatically.,	DBC446	DBC446, DBC43x	1	18 Reg.	40	300	
MAIN_TEXTS	T038b	Automatic SW server	Short for ""Do you want to retrieve the IP address of the software server automatically.,	DBC44	DBC44	1	16 Bold	30	218	
MAIN_TEXTS	T039	Auto SW server	Short for "Do you want to retrieve the IP address of the software server automatically.,	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	90	
MAIN_TEXTS	T042	SW Server	SW server with HTTP-protocol used for storing program for IP telephone.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T042b	SW Server	SW server with HTTP-protocol used for storing program for IP telephone.	DBC44	DBC44	1	16 Bold	25	168	
MAIN_TEXTS	T043	SWsrv	SW server with HTTP-protocol used for storing program for IP telephone.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	6	32	
MAIN_TEXTS	T044	Gatekeeper Discovery	Retrieve gatekeeper IPaddress with gatekeeper discovery.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T044b	Gatekeeper Discovery	Retrieve gatekeeper IPaddress with gatekeeper discovery.	DBC44	DBC44	1	16 Bold	30	218	
MAIN_TEXTS	T045	GK Discovery	Retrieve gatekeeper IPaddress with gatekeeper discovery.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	20	90	
MAIN_TEXTS	T048	GateKeeper	IP address for H.323gatekeeper (Server for RAS protocol) .	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T048b	GateKeeper	IP address for H.323gatekeeper (Server for RAS protocol) .	DBC44	DBC44	1	16 Bold	25	168	
MAIN_TEXTS	T049	GK	IP address for H.323gatekeeper (Server for RAS protocol).	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	6	32	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T050	Password	Password to be used when registering the telephone towards the gatekeeper.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T050b	Password	Password to be used when registering the telephone towards the gatekeeper.	DBC444	DBC444	1	16 Bold	25	218	
MAIN_TEXTS	T051	Password	Password to be used when registering the telephone towards the gatekeeper.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T052	Number:	Enter extension number.	DBC446	DBC446	1	18 Reg.	20	150	
MAIN_TEXTS	T052b	Number:	Enter extension number.	DBC43x	DBC43x	1	8 Reg.	20	64	
MAIN_TEXTS	T052c	Number:	Enter extension number.	DBC444	DBC444	1	16 Bold	20	104	
MAIN_TEXTS	T053	IP address:	IP v.4 address for telephone.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T053b	IP address:	IP v.4 address for telephone.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T053c	IP address:	IP v.4 address for telephone.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T054	Already in use! Enter new IP address.	The IP address is used by other equipment, enter new IP address.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T054b	Already in use! Enter new IP address.	The IP address is used by other equipment, enter new IP address.	DBC43x	DBC43x	2	8 Reg.	40	128	
MAIN_TEXTS	T054c	Already in use! Enter new IP address.	The IP address is used by other equipment, enter new IP address.	DBC444	DBC444	3	16 Bold	40	253	
MAIN_TEXTS	T055	Subnet mask:	IP v.4 subnet mask for the phone.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T055b	Subnet mask:	IP v.4 subnet mask for the phone.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T055c	Subnet mask:	IP v.4 subnet mask for the phone.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T056	Default gateway:	IP v.4 address for default gateway (router) to other network.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T056b	Default gateway:	IP v.4 address for default gateway (router) to other network.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T056c	Default gateway:	IP v.4 address for default gateway (router) to other network.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T057	Proxy Server	Proxy server used.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T057b	Proxy Server	Proxy server used.	DBC444	DBC444	1	16 Bold	20	200	
MAIN_TEXTS	T058	Proxy Server	Proxy server used.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T059	Proxy Address	Proxy server IP address.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T059b	Proxy Address	Proxy server IP address.	DBC444	DBC444	1	16 Bold	25	168	
MAIN_TEXTS	T060	Proxy	Proxy server IP address.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	6	32	
MAIN_TEXTS	T061	Proxy Port	Proxy server port number.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T061b	Proxy Port	Proxy server port number.	DBC444	DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T062	Proxy Port	Proxy server port number.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T064	Proxy port:	Enter port number for proxy server.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T064b	Proxy port:	Enter port number for proxy server.	DBC43x	DBC43x	1	8 Reg.	25	90	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T064c	Proxy port:	Enter port number for proxy server.	DBC444	DBC444	1	16 Bold	25	220	
MAIN_TEXTS	T065	User not logged on!	Extension has registered to the PBX.	DBC446	DBC446, DBC43x	1	18 Reg.	40	300	
MAIN_TEXTS	T065b	User not logged on!	Extension has not registered to the PBX.	DBC444	DBC444	1	16 Bold	30	165	
MAIN_TEXTS	T067	Log on with:	Enter your directory number.	DBC446	DBC446	1	18 Reg.	25	150	
MAIN_TEXTS	T067b	Log on with:	Enter your directory number.	DBC43x	DBC43x	1	8 Reg.	25	64	
MAIN_TEXTS	T067c	Log on with:	Enter your directory number.	DBC444	DBC444	1	16 Bold	25	198	
MAIN_TEXTS	T068	Password:	Enter your password for registering at the gatekeeper.	DBC446	DBC446	1	18 Reg.	25	150	
MAIN_TEXTS	T068b	Password:	Enter your password for registering at the gatekeeper.	DBC43x	DBC43x	1	8 Reg.	25	64	
MAIN_TEXTS	T068c	Password:	Enter your password for registering at the gatekeeper.	DBC444	DBC444	1	16 Bold	25	198	
MAIN_TEXTS	T069	Calling	Ongoing outgoing call.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T069b	Calling	Ongoing outgoing call.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T069c	Calling	Ongoing outgoing call.	DBC444	DBC444	1	14 Reg.	25	208	
MAIN_TEXTS	T070	Busy	The extension is occupied.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T070b	Busy	The extension is occupied.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T070c	Busy	The extension is occupied.	DBC444	DBC444	1	14 Reg.	25	208	
MAIN_TEXTS	T071	Incoming	Incoming call.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T071b	Incoming	Incoming call.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T071c	Incoming	Incoming call.	DBC444	DBC444	1	14 Reg.	25	208	
MAIN_TEXTS	T072	On hold	Line is on hold.	DBC446	DBC446	1	14 Bold	25	111	
MAIN_TEXTS	T072b	On hold	Line is on hold.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T074	Name:	Enter name.	DBC446	DBC446	1	18 Reg.	25	150	
MAIN_TEXTS	T074b	Name:	Enter name.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T074c	Name:	Enter name.	DBC444	DBC444	1	16 Bold	25	148	
MAIN_TEXTS	T075	Add	Add number to contacts.	DBC43x	DBC446, DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T075b	Add	Add number to contacts.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T076	Edit	Edit number in contacts.	DBC43x	DBC446, DBC43x	1	18 Reg.	25	128	
MAIN_TEXTS	T076b	Edit	Edit number in contacts.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T077	Delete	Delete from contacts.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T077b	Delete	Delete from contacts.	DBC444	DBC444	1	16 Bold	30	240	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T077c	Delete	Delete from contacts.	DBC446	DBC446	1	18 Bold	25	460	
MAIN_TEXTS	T078	No calls in CallList!	Call list is empty.	DBC446	DBC446, DBC43x	1	18 Reg.	40	468	
MAIN_TEXTS	T078b	No calls in CallList!	Call list is empty.	DBC444	DBC444	3	16 Bold	40	253	
MAIN_TEXTS	T079	No calls in CallList!	Call list is empty.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T080	New time:	Enter new time.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T080b	New time:	Enter new time.	DBC43x	DBC43x	1	8 Reg.	25	64	
MAIN_TEXTS	T080c	New time:	Enter new time.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T081	New date:	Enter new date.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T081b	New date:	Enter new date.	DBC43x	DBC43x	1	8 Reg.	25	64	
MAIN_TEXTS	T081c	New date:	Enter new date.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T082	New number:	Enter extension number or procedure. For use when programming shortcut keys.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T082b	New number:	Enter extension number or procedure. For use when programming shortcut keys.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	64	
MAIN_TEXTS	T083	Line * key	Key for access line 1and 2. * is locally replaced by the line number.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T083b	Line * key	Key for access line 1and 2. * is locally replaced by the line number.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T084	Settings key	Key for entering and exiting settings mode.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	30	220	
MAIN_TEXTS	T086	Menu key	Key for toggling between WAP service mode and local mode.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T086b	Menu key	Key for toggling between WAP service mode and local mode.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T087	Transfer key	Key for request a transfer.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T087b	Transfer key	Key for request a transfer.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T088	Free on 2nd line key	Key for request free on 2nd line.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	30	220	
MAIN_TEXTS	T090	Follow-me key	Key for request follow-me.	DBC446	DBC446, DBC444	1	18 Reg.	30	220	
MAIN_TEXTS	T092	Call back key	Key for request callback.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T092b	Call back key	Key for request callback.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T093	Message waiting key	Key for request fetch of message.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	30	220	
MAIN_TEXTS	T095	Conference key	Key for request conference.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T095b	Conference key	Key for request conference.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T096	Call list key	Key for entering and exiting call list mode.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T096b	Call list key	Key for entering and exiting call list mode.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T097	Inquiry key	Key for inquiry line.	DBC446	DBC446	1	18 Reg.	25	220	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T097b	Inquiry key	Key for inquiry line.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T098	Cannot be changed	The key cannot be changed.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	30	220	
MAIN_TEXTS	T099	Cannot be changed	The key cannot be changed.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T100	Error:	Debug printout. Error found.	DBC446	DBC446	1	18 Reg.	10	100	
MAIN_TEXTS	T100b	Error:	Debug printout. Error found.	DBC43x	DBC43x	1	8 Reg.	10	60	
MAIN_TEXTS	T100c	Error:	Debug printout. Error found.	DBC444	DBC444	1	16 Bold	10	100	
MAIN_TEXTS	T105	ConfigFile	Error source, Config file.	DBC446	DBC446	1	18 Reg.	15	150	
MAIN_TEXTS	T105b	ConfigFile	Error source, Config file.	DBC43x	DBC43x	1	8 Reg.	15	64	
MAIN_TEXTS	T105c	ConfigFile	Error source, Config file.	DBC444	DBC444	1	16 Bold	20	190	
MAIN_TEXTS	T106	Server IP address:	Enter IP address for SW server.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T106b	Server IP address:	Enter IP address for SW server.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T106c	Server IP address:	Enter IP address for SW server.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T107	Proxy IP address:	Enter IP address for proxy server.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T107b	Proxy IP address:	Enter IP address for proxy server.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T107c	Proxy IP address:	Enter IP address for proxy server.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T108	Please wait...	Please wait for a while.	DBC446	DBC446	1	18 Reg.	30	220	
MAIN_TEXTS	T108b	Please wait...	Please wait for a while.	DBC43x	DBC43x	1	8 Reg.	30	128	
MAIN_TEXTS	T108c	Please wait...	Please wait for a while.	DBC444	DBC444	1	16 Bold	30	258	
MAIN_TEXTS	T110	Log off?	Question to log off.	DBC446	DBC446	1	24 Bold	30	267	
MAIN_TEXTS	T110b	Log off?	Question to log off.	DBC43x	DBC43x	1	8Reg.	30	128	
MAIN_TEXTS	T110c	Log off?	Question to log off.	DBC444	DBC444	1	16 Bold	30	253	
MAIN_TEXTS	T111	Time & date not set	Indication instead of time if not set.	DBC446	DBC446	1	14 Bold	22	119	
MAIN_TEXTS	T111b	Time & date not set	Indication instead of time if not set.	DBC43x	DBC43x	1	8 Reg.	22	75	
MAIN_TEXTS	T111c	Time & date not set	Indication instead of time if not set.	DBC444	DBC444	1	16 Reg.	22	150	
MAIN_TEXTS	T112	RESTARTING	The telephone is rebooting.	DBC446	DBC446	1	24 Bold	30	466	
MAIN_TEXTS	T112b	RESTARTING	The telephone is rebooting.	DBC43x	DBC43x	1	8 Bold	30	128	
MAIN_TEXTS	T112c	RESTARTING	The telephone is rebooting.	DBC444	DBC444	3	16 Bold	30	258	
MAIN_TEXTS	T125	Corporate directory	Access the corporate directory.	DBC446	DBC446	1	16 Bold	40	446	
MAIN_TEXTS	T125b	Corporate directory	Access the corporate directory.	DBC43x	DBC43x	1	8 Reg.	40	128	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T125c	Corporate directory	Access the corporate directory.	DBC444	DBC444	1	16 Bold	40	270	
MAIN_TEXTS	T126	No connection to network!	No connection to network.	DBC446	DBC446, DBC43x	1	18 Bold	40	466	
MAIN_TEXTS	T126b	No connection to network!	No connection to network.	DBC444	DBC444	2	16 Bold	40	258	
MAIN_TEXTS	T127	Error! No Network!	No connection to network.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T128	Display Menus	Language of the display menus texts.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T128b	Display Menus	Language of the display menus texts.	DBC43x	DBC43x	1	8 Reg.	25	70	
MAIN_TEXTS	T128c	Display Menus	Language of the display menus texts.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T129	Keypad Characters	Language of the keypad characters.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T129b	Keypad Characters	Language of the keypad characters.	DBC43x	DBC43x	1	8 Reg.	25	70	
MAIN_TEXTS	T129c	Keypad Characters	Language of the keypad characters.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T139	Boot	Boot.	DBC446	DBC446	1	18 Reg.	20	150	
MAIN_TEXTS	T139b	Boot	Boot.	DBC43x	DBC43x	1	8 Reg.	20	70	
MAIN_TEXTS	T139c	Boot	Boot.	DBC444	DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T140	Application	Application.	DBC446	DBC446	1	18 Reg.	20	150	
MAIN_TEXTS	T140b	Application	Application.	DBC43x	DBC43x	1	8 Reg.	20	70	
MAIN_TEXTS	T140c	Application	Application.	DBC444	DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T141	Add to contacts	Add to contacts (Webserver).	DBC446	DBC446	1	18 Reg.	40	180	
MAIN_TEXTS	T141b	Add to contacts	Add to contacts (Webserver).	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T141c	Add to contacts	Add to contacts (phone/Webserver).	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T142	Delete contact	Delete contacts (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T142b	Delete contacts	Delete contacts (Webserver).	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T143	Delete call list	Delete call list (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T143b	Delete call list	Delete call list (Webserver).	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T143c	Delete call list	Delete call list (Webserver).	DBC444	DBC444	1	8 Reg.	30	240	
MAIN_TEXTS	T144	Change password	Change password (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T144b	Change password	Change password (Webserver).	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T145	New password	New password (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T145b	New password	New password (Webserver).	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T146	Confirm password	Confirm password (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T146b	Confirm password	Confirm password (Webserver).	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T147	Invalid password	Invalid password (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T147b	Invalid password	Invalid password (Webserver).	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T147c	Invalid password	Invalid password (Phone/Webserver).	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T148	(6-20 characters)	(6-20 characters) (Webserver).	DBC446	DBC446	1	8 Reg.	40	300	
MAIN_TEXTS	T148b	(6-20 characters)	(6-20 characters) (Webserver).	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T150	My Profile	My profile menu.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T150b	My Profile	My profile menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T150c	My Profile	My profile menu.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T151	Follow-me	Follow-me menu.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T151b	Follow-me	Follow-me menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T151c	Follow-me	Follow-me menu or label of Follow-me key	DBC444	DBC444	2	14 Bold, Cond.	25	66	
MAIN_TEXTS	T152	External Follow-me	External follow-me menu.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T152b	External Follow-me	External follow-me menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T152c	External Follow-me	External follow-me menu.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T154	Available	Absence reason not set.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T154b	Available	Absence reason not set.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T154c	Available	Absence reason not set.	DBC444	DBC444	1	16 Bold	25	275	
MAIN_TEXTS	T155	Lunch	Absence reason: Lunch	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T155b	Lunch	Absence reason: Lunch	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T155c	Lunch	Absence reason: Lunch	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T156	Busy	Absence reason: Busy	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T156b	Busy	Absence reason: Busy	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T156c	Busy	Absence reason: Busy	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T157	Absent	Absence reason: Absent	DBC446	DBC446	1	18 Reg.	25	271	
MAIN_TEXTS	T157b	Absent	Absence reason: Absent	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T157c	Absent	Absence reason: Absent	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T158	Meeting	Absence reason: Meeting	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T158b	Meeting	Absence reason: Meeting	DBC43x	DBC43x	1	8 Reg.	25	80	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T158c	Meeting	Absence reason: Meeting	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T159	Trip	Absence reason: Trip.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T159b	Trip	Absence reason: Trip.	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T159c	Trip	Absence reason: Trip.	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T160	Course	Absence reason: Course	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T160b	Course	Absence reason: Course	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T160c	Course	Absence reason: Course	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T161	Vacation	Absence reason: Vacation	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T161b	Vacation	Absence reason: Vacation	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T161c	Vacation	Absence reason: Vacation	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T162	Day Off	Absence reason: DayOff	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T162b	Day Off	Absence reason: DayOff	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T162c	Day Off	Absence reason: DayOff	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T163	Gone Home	Absence reason: GoneHome	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T163b	Gone Home	Absence reason: GoneHome	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T163c	Gone Home	Absence reason: GoneHome	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T164	Illness	Absence reason: Illness	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T164b	Illness	Absence reason: Illness	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T164c	Illness	Absence reason: Illness	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T165	Special	Absence reason: Special	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T165b	Special	Absence reason: Special	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T165c	Special	Absence reason: Special	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T166	Official Matter	Absence reason: OfficialMatter	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T166b	Official Matter	Absence reason: OfficialMatter	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T166c	Official Matter	Absence reason: OfficialMatter	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T167	Free Time	Absence reason: FreeTime	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T167b	Free Time	Absence reason: FreeTime	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T167c	Free Time	Absence reason: FreeTime	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T168	Parental Leave	Absence reason: ParentalLeave	DBC446	DBC446	1	18 Reg.	25	463	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T168b	Parental Leave	Absence reason: Parental Leave	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T168c	Parental Leave	Absence reason: Parental Leave	DBC44	DBC44	1	16 Bold	25	268	
MAIN_TEXTS	T169	Profile number:	Enter profile number.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T169b	Profile number:	Enter profile number.	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T169c	Profile number:	Enter profile number.	DBC44	DBC44	1	16 Bold	30	220	
MAIN_TEXTS	T170	Return time	Enter return time.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T170b	Return time	Enter return time.	DBC43x	DBC43x	1	8 Reg.	25	60	
MAIN_TEXTS	T170c	Return time	Enter return time.	DBC44	DBC44	1	16 Bold	25	166	
MAIN_TEXTS	T171	Return date	Enter return date.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T171b	Return date	Enter return date.	DBC43x	DBC43x	1	8 Reg.	25	60	
MAIN_TEXTS	T171c	Return date	Enter return date.	DBC44	DBC44	1	16 Bold	25	166	
MAIN_TEXTS	T180	Option Unit	Option unit menu.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T180b	Option Unit	Option unit menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T180c	Option Unit	Option unit menu.	DBC44	DBC44	1	16 Bold	25	270	
MAIN_TEXTS	T181	Extra Bell	Extra bell on option unit.	DBC446	DBC446	1	14 Reg.	25	400	
MAIN_TEXTS	T181b	Extra Bell	Extra bell on option unit.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T181c	Extra Bell	Extra bell on option unit.	DBC44	DBC44	1	16 Bold	25	296	
MAIN_TEXTS	T182	Busy Signal	Busy signal on option unit.	DBC446	DBC446	1	14 Reg.	25	400	
MAIN_TEXTS	T182b	Busy Signal	Busy signal on option unit.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T182c	Busy Signal	Busy signal on option unit.	DBC44	DBC44	1	16 Bold	25	296	
MAIN_TEXTS	T183	Combined Bell/Busy	Combined bell/busy signal on option unit.	DBC446	DBC446	1	14 Reg.	25	400	
MAIN_TEXTS	T183b	Combined Bell/Busy	Combined bell/busy signal on option unit.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T183c	Combined Bell/Busy	Combined bell/busy signal on option unit.	DBC44	DBC44	1	16 Bold	25	296	
MAIN_TEXTS	T185	For SOS calls, dial *	For SOS calls, dial * is locally replaced by the emergency number.	DBC446	DBC446, DBC43x	1	14 Bold	30	378	
MAIN_TEXTS	T185b	For SOS calls, dial *	For SOS calls, dial * is locally replaced by the emergency number.	DBC44	DBC44	2	16 Bold	30	253	
MAIN_TEXTS	T186	* calls only	For SOS calls, dial * is locally replaced by the emergency number.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	64	
MAIN_TEXTS	T191	Call Pick-Up key	Key for request call pick-up.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T191b	Call Pick-Up key	Key for request call pick-up.	DBC43x	DBC43x, DBC44	1	8 Reg.	25	128	
MAIN_TEXTS	T192	Call Waiting key	Key for request call waiting.	DBC446	DBC446	1	18 Reg.	25	220	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T192b	Call Waiting key	Key for request call waiting.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T193	Intrusion key	Key for request intrusion.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T193b	Intrusion key	Key for request intrusion.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T194	Type of ring signal	The type of ring signal used for incoming call on supervised key.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T194b	Type of ring signal	The type of ring signal used for incoming call on supervised key.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T195	Silence	Silent ringing.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T195b	Silence	Silent ringing.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T196	Periodic	Normal periodic ringing.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T196b	Periodic	Normal periodic ringing.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T196c	Periodic	Normal periodic ringing.	DBC444	DBC444	1	16 Bold	25	150	
MAIN_TEXTS	T197	Delayed Periodic	Start periodic ringing after a delay.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T197b	Delayed Periodic	Start periodic ringing after a delay.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T197c	Delayed Periodic	Start periodic ringing after a delay.	DBC444	DBC444	1	16 Bold	25	150	
MAIN_TEXTS	T198	One Muted	Only one ring period with low level.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T198b	One Muted	Only one ring period with low level.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T198c	One Muted	Only one ring period with low level.	DBC444	DBC444	1	16 Bold	25	150	
MAIN_TEXTS	T199	Delayed One Muted	Start one muted ringing after a delay.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T199b	Delayed One Muted	Start one muted ringing after a delay.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T199c	Delayed One Muted	Start one muted ringing after a delay.	DBC444	DBC444	1	16 Bold	25	150	
MAIN_TEXTS	T206	VLAN for phone port	Use VLAN (virtual LAN) for the phone port (Manually/Automatically).	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T206b	VLAN for phone port	Use VLAN (virtual LAN) for the phone port (Manually/Automatically).	DBC444	DBC444	1	16 Bold	30	230	
MAIN_TEXTS	T207	VLAN for phone	Use VLAN for the telephone port (Manually/Automatically).	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T208	Phone Port VID	VLAN ID for the telephone port.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T208b	Phone Port VID	VLAN ID for the telephone port.	DBC444	DBC444	1	16 Bold	25	202	
MAIN_TEXTS	T209	Phone Port VID	VLAN ID for the telephone port.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T210	VLAN for PC Port	Use VLAN for PC port (Manually/Automatically).	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T210b	VLAN for PC Port	Use VLAN for PC port (Manually/Automatically).	DBC444	DBC444	1	16 Bold	30	230	
MAIN_TEXTS	T211	VLAN for PC	Use VLAN for PC port (Manually/Automatically).	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T212	PC Port VID	VLAN ID for PC port.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T212b	PC Port VID	VLAN ID for PC port.	DBC444	DBC444	1	16 Bold	25	202	
MAIN_TEXTS	T213	PC Port VID	VLAN ID for PC port.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T215	Man	Manual.	DBC446	DBC446	1	18 Reg.	6	60	
MAIN_TEXTS	T215b	Man	Manual.	DBC43x	DBC43x	1	8 Reg.	6	40	
MAIN_TEXTS	T215c	Man	Manual.	DBC444	DBC444	1	16 Bold	6	40	
MAIN_TEXTS	T216	Status key	Key on which the LED indicates network/logon status.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T217	Backlight	Display backlight menu.	DBC446	DBC446	1	18 Reg.	25	144	
MAIN_TEXTS	T217b	Backlight	Display backlight menu.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T218	OMD	OMD menu.	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T218b	OMD	OMD menu.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T218c	OMD	OMD menu.	DBC444	DBC444	1	16 Bold	25	218	
MAIN_TEXTS	T219	Use OMD mode:	Question to use OMD mode.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T220	LAN access control	LAN access control menu.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T220b	LAN access control	LAN access control menu.	DBC444	DBC444	1	16 Bold	25	230	
MAIN_TEXTS	T221	LAN access ctrl.	LAN access control menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T222	User ID:	Enter user ID for LAN access control.	DBC446	DBC446	1	18 Reg.	25	150	
MAIN_TEXTS	T222b	User ID:	Enter user ID for LAN access control.	DBC43x	DBC43x	1	8 Reg.	25	64	
MAIN_TEXTS	T222c	User ID:	Enter user ID for LAN access control.	DBC444	DBC444	1	16 Bold	25	198	
MAIN_TEXTS	T223	Unable to log on!	Unable to log on!	DBC446	DBC446	1	18 Bold	25	466	
MAIN_TEXTS	T223b	Unable to log on!	Unable to log on!	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T223c	Unable to log on!	Unable to log on!	DBC444	DBC444	1	16 Bold	25	253	
MAIN_TEXTS	T224	Check User ID/Password	CheckUser ID/Password.	DBC446	DBC446	1	18 Bold	25	466	
MAIN_TEXTS	T224b	Check User ID/Password	CheckUser ID/Password.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T224c	Check User ID/Password	CheckUser ID/Password.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T225	Auto	Automatic.	DBC446	DBC446	1	18 Reg.	6	60	
MAIN_TEXTS	T225b	Auto	Automatic.	DBC43x	DBC43x	1	8 Reg.	6	30	
MAIN_TEXTS	T225c	Auto	Automatic.	DBC444	DBC444	1	16 Bold	6	40	
MAIN_TEXTS	T226	Automatic SIP server	Choose automatic SIP server: Yes/No.	DBC446	DBC446, DBC43x	1	18 Reg.	30	300	
MAIN_TEXTS	T226b	Automatic SIP server	Choose automatic SIP server: Yes/No.	DBC444	DBC444	1	16 Bold	30	218	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T227	Auto SIP server:	Choose automatic SIP server: Yes/No.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T230	SIP Proxy Server	SIP Proxy server IP-address.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T230b	SIP Proxy Server	SIP Proxy server IP-address.	DBC444	DBC444	1	16 Bold	25	168	
MAIN_TEXTS	T231	SIP	SIP Proxy server IP-address.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	6	32	
MAIN_TEXTS	T232	Protocol:	Choose protocol: Auto/H323/SIP.	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T232b	Protocol:	Choose protocol: Auto/H323/SIP.	DBC43x	DBC43x	1	8 Reg.	25	80	
MAIN_TEXTS	T232c	Protocol:	Choose protocol: Auto/H323/SIP.	DBC444	DBC444	1	16 Bold	25	250	
MAIN_TEXTS	T233	Protocol	Protocol (Auto(H323/SIP)) menu.	DBC446	DBC446	1	18 Reg.	20	300	
MAIN_TEXTS	T233b	Protocol	Protocol (Auto(H323/SIP)) menu.	DBC43x	DBC43x	1	8 Reg.	20	70	
MAIN_TEXTS	T233c	Protocol	Protocol (Auto(H323/SIP)) menu.	DBC444	DBC444	1	16 Bold	20	238	
MAIN_TEXTS	T234	H323	H323 choice in T233.	DBC446	DBC446	1	18 Reg.	6	60	
MAIN_TEXTS	T234b	H323	H323 choice in T233.	DBC43x	DBC43x	1	8 Reg.	6	40	
MAIN_TEXTS	T234c	H323	H323 choice in T233.	DBC444	DBC444	1	16 Bold	6	40	
MAIN_TEXTS	T235	SIP	SIP choice in T233.	DBC446	DBC446	1	18 Reg.	6	60	
MAIN_TEXTS	T235b	SIP	SIP choice in T233.	DBC43x	DBC43x	1	8 Reg.	6	40	
MAIN_TEXTS	T235c	SIP	SIP choice in T233.	DBC444	DBC444	1	16 Bold	6	40	
MAIN_TEXTS	T236	SIP Proxy Port	SIP Proxy Port (12345) menu.	DBC446	DBC446, DBC43x	1	18 Reg.	25	300	
MAIN_TEXTS	T236b	SIP Proxy Port	SIP Proxy Port (12345) menu.	DBC444	DBC444	1	16 Bold	25	250	
MAIN_TEXTS	T237	SIP Port	SIP Proxy Port (12345) menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	90	
MAIN_TEXTS	T238	SIP port:	Enter port number for SIP proxy server.	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T238b	SIP port:	Enter port number for SIP proxy server.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T238c	SIP port:	Enter port number for SIP proxy server.	DBC444	DBC444	1	16 Bold	25	220	
MAIN_TEXTS	T239	Security mismatch!	The VoIP security settings in the telephone does not correspond to the security settings in the PBX.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T239b	Security mismatch!	The VoIP security settings in the telephone does not correspond to the security settings in the PBX.	DBC43x	DBC43x	1	8 Reg.	40	128	
MAIN_TEXTS	T239c	Security mismatch!	The VoIP security settings in the telephone does not correspond to the security settings in the PBX.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T240	Contact system administrator	The end-user shall contact the system administrator to get the problem solved.	DBC446	DBC446, DBC43x	1	14 Bold	40	360	
MAIN_TEXTS	T240b	Contact system administrator	The end-user shall contact the system administrator to get the problem solved.	DBC444	DBC444	2	16 Bold	40	253	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T241	Contact system admin	The end-user shall contact the system administrator to get the problem solved.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	40	128	
MAIN_TEXTS	T242	Information	Information menu.	DBC446	DBC446	1	18 Reg.	25	463	
MAIN_TEXTS	T242b	Information	Information menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T242c	Information	Information menu.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T244	Call tracing	Function key used to initiate malicious call tracing.	DBC446	DBC446	1	14 Reg.	25	200	
MAIN_TEXTS	T244b	Call tracing	Function key used to initiate malicious call tracing.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T244c	Call tracing	Function key used to initiate malicious call tracing.	DBC444	DBC444	2	14 Bold, Cond.	25	66	
MAIN_TEXTS	T247	Getting network settings!	Shown when phone gets IPaddress via DHCP.	DBC446	DBC446	1	18 Reg.	40	466	
MAIN_TEXTS	T247b	Getting network settings!	Shown when phone gets IPaddress via DHCP.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T247c	Getting network settings!	Shown when phone gets IPaddress via DHCP.	DBC444	DBC444	3	16 Bold	40	258	
MAIN_TEXTS	T248	Failed to get network settings!	Shown if phone failes toget IP address via DHCP.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T248b	Failed to get network settings!	Shown if phone failes toget IP address via DHCP.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T248c	Failed to get network settings!	Shown if phone failes toget IP address via DHCP.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T249	Telephone	Phone	DBC446	DBC446	1	18 Reg.	40	330	
MAIN_TEXTS	T249b	Telephone	Phone	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T250	Getting telephone settings!	Shown when phone gets the configuration file.	DBC446	DBC446	1	18 Reg.	40	466	
MAIN_TEXTS	T250b	Getting telephone settings!	Shown when phone gets the configuration file.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T250c	Getting telephone settings!	Shown when phone gets the configuration file.	DBC444	DBC444	2	16 Bold	40	258	
MAIN_TEXTS	T251	A new version of telephone software is available.	Shown if new software is available.	DBC446	DBC446, DBC43x	1	18 Reg.	60	466	
MAIN_TEXTS	T251b	A new version of telephone software is available.	Shown if new software is available.	DBC444	DBC444	2	16 Bold	60	253	
MAIN_TEXTS	T252	Update is recommended (select Yes).	Shown if new software is available.	DBC446	DBC446, DBC43x	1	18 Reg.	40	466	
MAIN_TEXTS	T252b	Update is recommended (select Yes).	Shown if new software is available.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T253	Updating telephone software.	Shown while updating the software.	DBC446	DBC446, DBC43x	1	18 Reg.	40	466	
MAIN_TEXTS	T253b	Updating telephone software.	Shown while updating the software.	DBC444	DBC444	2	16 Bold	40	258	
MAIN_TEXTS	T254	Failed to update software!	Shown if update of software fails.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T254b	Failed to update software!	Shown if update of software fails.	DBC43x	DBC43x	1	8 Reg.	40	128	
MAIN_TEXTS	T254c	Failed to update software!	Shown if update of software fails.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T255	VLAN ID (1-4095), Phone:	Enter VLAN ID for Phone (LAN) port.	DBC446	DBC446, DBC43x	1	14 Reg.	30	220	
MAIN_TEXTS	T255b	VLAN ID (1-4095), Phone:	Enter VLAN ID for Phone (LAN) port.	DBC444	DBC444	1	16 Bold	30	220	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T257	VLAN ID (1-4095), PC:	Enter VLAN ID for PC port.	DBC446	DBC446, DBC43x	1	18 Reg.	30	220	
MAIN_TEXTS	T257b	VLAN ID (1-4095), PC:	Enter VLAN ID for PC port.	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T259	Line *	Shown on line button 1 and 2. * is replaced with line number.	DBC446	DBC444, DBC446	1	14 Bold	10	100	
MAIN_TEXTS	T259b	Line *	Shown the line which is On hold. * is replaced with line number.	DBC43x	DBC43x	1	8 Reg.	6	50	
MAIN_TEXTS	T260	Inquiry	Shown on inquiry button.	DBC446	DBC446, DBC43x, DBC444	1	14 Bold	10	100	
MAIN_TEXTS	T261	My Settings	My Settings menu.	DBC446	DBC446, DBC43x	1	18 Reg.	40	468	
MAIN_TEXTS	T261b	My Settings	My Settings menu.	DBC444	DBC444	1	16 Bold	40	270	
MAIN_TEXTS	T262	Applications and Settings	Application and settings menu.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	40	468	
MAIN_TEXTS	T263	Current address:	Current IP address.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T263b	Current address:	Current IP address.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T263c	Current address:	Current IP address.	DBC444	DBC444	1	16 Bold	25	140	
MAIN_TEXTS	T264	Current port:	Current IP port number.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T264b	Current port:	Current IP port number.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T264c	Current port:	Current IP port number.	DBC444	DBC444	1	16 Bold	25	140	
MAIN_TEXTS	T267	Message Waiting	Message Waiting menu.	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T267b	Message Waiting	Message Waiting menu.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T268	Voice Mailbox	Voice mail menu.	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T268b	Voice Mailbox	Voice mail menu.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T269	Message Waiting number:	Number to the Message Waiting service.	DBC446	DBC446	1	18 Reg.	40	300	
MAIN_TEXTS	T269b	Message Waiting number:	Number to the Message Waiting service.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	70	
MAIN_TEXTS	T270	Voice Mailbox number:	Number to the Voice Mailbox service.	DBC446	DBC446	1	18 Reg.	40	300	
MAIN_TEXTS	T270b	Voice Mailbox number:	Number to the Voice Mailbox service.	DBC43x	DBC43x, DBC444	1	8 Reg.	40	70	
MAIN_TEXTS	T271	Accounts	Shows with account isused.	DBC446	DBC446, DBC43x, DBC444	1	14 Bold	40	320	
MAIN_TEXTS	T272	Administrator Settings	Administrator settings menu.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	40	468	
MAIN_TEXTS	T273	Duplicated IP address!	The IP address is duplicated on the network, used by someone else.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T273b	Duplicated IP address!	The IP address is duplicated on the network, used by someone else.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T273c	Duplicated IP address!	The IP address is duplicated on the network, used by someone else.	DBC444	DBC444	2	16 Bold	40	258	
MAIN_TEXTS	T274	My Services Settings	Used for accessing my services setting page.	DBC446	DBC446, DBC43x, DBC444	1	18 Reg.	40	468	
MAIN_TEXTS	T275	Secure SIP Proxy Port	Secure SIP Proxy Port (12345) menu.	DBC446	DBC446, DBC43x	1	18 Reg.	40	360	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T275b	Secure SIP Proxy Port	Secure SIP Proxy Port (12345) menu.	DBC444	DBC444	1	16 Bold	40	250	
MAIN_TEXTS	T276	Secure SIP Port	Secure SIP Proxy Port (12345) menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T277	Secure SIP port:	Enter secure port number for SIP proxy server.	DBC446	DBC446, DBC43x	1	18 Reg.	40	220	
MAIN_TEXTS	T277b	Secure SIP port:	Enter secure port number for SIP proxy server.	DBC444	DBC444	1	16 Bold	40	250	
MAIN_TEXTS	T278	Old PIN:	Enter your old Personal Identification Number, at changing of the PIN.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T278b	Old PIN:	Enter your old Personal Identification Number, at changing of the PIN.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T279	New PIN:	Enter your new PIN, at changing of the PIN.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T279b	New PIN:	Enter your new PIN, at changing of the PIN.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T280	Confirm your new PIN:	Enter your new PIN again, at changing of the PIN.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T280b	Confirm your new PIN:	Enter your new PIN again, at changing of the PIN.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	90	
MAIN_TEXTS	T282	Change PIN	Change your Personal Identification Number	DBC446	DBC446	1	18 Bold	40	468	
MAIN_TEXTS	T282b	Change PIN	Change your Personal Identification Number	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T282c	Change PIN	Change your Personal Identification Number	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T283	PINs mismatch!	The new PIN does not match with the confirmation PIN.	DBC446	DBC446	1	18 Bold	40	468	
MAIN_TEXTS	T283b	PINs mismatch!	The new PIN does not match with the confirmation PIN.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T283c	PINs mismatch!	The new PIN does not match with the confirmation PIN.	DBC444	DBC444	2	16 Bold	40	253	
MAIN_TEXTS	T284	PIN:	Enter your Personal Identification Number	DBC446	DBC446	1	18 Reg.	40	150	
MAIN_TEXTS	T284b	PIN:	Enter your Personal Identification Number	DBC43x	DBC43x	1	8 Reg.	6	32	
MAIN_TEXTS	T284c	PIN:	Enter your Personal Identification Number	DBC444	DBC444	1	16 Bold	40	198	
MAIN_TEXTS	T285	Change PIN succeeded!	The change of the Personal Identification Number was successful.	DBC446	DBC446	1	18 Bold	40	468	
MAIN_TEXTS	T285b	Change PIN succeeded!	The change of the Personal Identification Number was successful.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T285c	Change PIN succeeded!	The change of the Personal Identification Number was successful.	DBC444	DBC444	2	16 Bold	40	178	
MAIN_TEXTS	T286	The old PIN is not correct!	The entered old PIN is not correct, at changing of PIN.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T286b	The old PIN is not correct!	The entered old PIN is not correct, at changing of PIN.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T288	The max length of PIN is 7	Max number of digits in the PIN are seven.	DBC446	DBC446	1	18 Reg.	40	220	
MAIN_TEXTS	T288b	The max length of PIN is 7	Max number of digits in the PIN are seven.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T289	PIN or Password	Enter your pin or password. (Web server).	DBC446	DBC446	1	8 Reg.	25	300	
MAIN_TEXTS	T289b	PIN or Password	Enter your pin or password. (Web server).	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T289c	PIN or Password	Enter your pin or password. (Web server).	DBC444	DBC444	1	8 Reg.	25	300	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T290	Feature is not available!	Feature is not available. (Web server).	DBC446	DBC446	1	8 Reg.	25	300	
MAIN_TEXTS	T290b	Feature is not available!	Feature is no available. (Web server).	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T290c	Feature is not available!	Feature is no available. (Web server).	DBC444	DBC444	1	8 Reg.	25	300	
MAIN_TEXTS	T291	Anonymous	Anonymous call in Call list.	DBC446	DBC446	1	18 Reg.	24	220	
MAIN_TEXTS	T291b	Anonymous	Anonymous call in Call list.	DBC43x	DBC43x	1	8 Reg.	24	120	
MAIN_TEXTS	T291c	Anonymous	Anonymous call in Call list.	DBC444	DBC444	1	16 Bold	24	150	
MAIN_TEXTS	T294	Add:	Add one more entry.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	15	70	
MAIN_TEXTS	T295	Delete:	Delete an entry.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	15	70	
MAIN_TEXTS	T296	Delete all calls in list	Delete all the entries in call list.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T296b	Delete all calls in list	Delete all the entries in call list.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T296c	Delete all calls in list	Delete all the entries in call list.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T297	Exit Call List	Exit from the call list.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T297b	Exit Call List	Exit from the call list.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T297c	Exit Call List	Exit from the call list.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T298	Details:	Details.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	70	
MAIN_TEXTS	T299	Set Time Format to:	Confirm the time format setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T300	Set Date Format to:	Confirm the date format setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T301	My Availability	This is the presence and availability.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T301b	My Availability	This is the presence and availability.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T301c	My Availability	This is the presence and availability.	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T302	My mobile phone	My mobile phone number.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T302b	My mobile phone	My mobile phone number.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T302c	My mobile phone	My mobile phone number.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T304	Set Display menus to:	Language for the menu displaying on the screen.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T305	Keypad	Keypad setting for different languages.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	15	70	
MAIN_TEXTS	T306	Set Keypad character sto:	Confirm the keypad characters setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T307	Format	The time or date format setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T308	Display	Display settings.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T308b	Display	Display settings.	DBC444	DBC444	1	16 Bold	25	270	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T308c	Display	Display settings.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T309	Set Phone Contrast?	The confirmation of phone contrast setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T310	Hold time	Specify the brightness hold time.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T311	Set Hold time to:	The confirmation of brightness hold time.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T312	Brightness Hold time	The brightness hold time setting.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T312b	Brightness Hold time	The brightness hold time setting.	DBC444	DBC444	1	16 Bold	25	204	
MAIN_TEXTS	T312c	Brightness Hold time	The brightness hold time setting.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T313	minute(s)	The time of brightness hold in minute(s).	DBC43x	DBC43x	1	8 Reg.	10	40	
MAIN_TEXTS	T313b	minute(s)	The time of brightness hold in minute(s).	DBC444	DBC444	1	16 Bold	10	80	
MAIN_TEXTS	T313c	minute(s)	The time of brightness hold in minute(s).	DBC446	DBC446	1	14 Bold	20	220	
MAIN_TEXTS	T314	Phone Brightness	The phone brightness setting.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T314b	Phone Brightness	The phone brightness setting.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T314c	Phone Brightness	The phone brightness setting.	DBC446	DBC446	2	18 Reg.	25	144	
MAIN_TEXTS	T316	Set Phone Brightness?	The confirmation of phone brightness setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T317	Ring:	Indication of the ring signal	DBC43x	DBC43x	1	8 Reg.	6	32	
MAIN_TEXTS	T317b	Ring:	Indication of the ring signal	DBC444	DBC444	1	16 Bold	6	60	
MAIN_TEXTS	T317c	Ring:	Indication of the ring signal	DBC446	DBC446	1	18 Reg.	10	100	
MAIN_TEXTS	T318	Ring Signal	Ring signal setting.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T318b	Ring Signal	Ring signal setting.	DBC444	DBC444	1	16 Bold	25	190	
MAIN_TEXTS	T318c	Ring Signal	Ring signal setting.	DBC446	DBC446	1	18 Reg.	25	220	
MAIN_TEXTS	T320	Play	Play back the ringsignal.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T322	Edit Name	Edit name in the contacts.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T323	Edit Number	Edit number in the contacts.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T324	Edit Ring	Edit the corresponding ring signal.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T324b	Edit Ring	Edit the corresponding ring signal.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T325	Exit Add to Contacts	Exit add an new entry to the contacts.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T325b	Exit Add to Contacts	Exit add an new entry to the contacts.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T325c	Exit Add to Contacts	Exit add an new entry to the contacts.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T327	Ring Signals	Ring signal settings.	DBC43x	DBC43x	1	8 Reg.	25	120	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T327b	Ring Signals	Ring signal settings.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T327c	Ring Signals	Ring signal settings.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T329	Set Default Ring Signa to:	The confirmation of default ring tone.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T332	Sounds	Sounds settings.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T332b	Sounds	Sounds settings.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T332c	Sounds	Sounds settings.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T333	Default Ring Signal	Default ring signal setting.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T333b	Default Ring Signal	Default ring signal setting.	DBC444	DBC444	1	16 Bold	25	296	
MAIN_TEXTS	T333c	Default Ring Signal	Default ring signal setting.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T334	Software update available.	There is available new software.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T335	Update?	Is the software update the software accepted?	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T336	Updating phone software.	Software update in progress.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T337	Erase	Erase one digit from the end of the string.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T338	Erase all	Erase all digits in a String.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T339	Cancel log on	Cancel log on.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T339b	Cancel log on	Cancel log on.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T339c	Cancel log on	Cancel log on.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T340	Back to Log On with	Go back to the log on page.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T340b	Back to Log On with	Go back to the log on page.	DBC444	DBC444, DBC446	1	16 Bold	30	240	
MAIN_TEXTS	T341	No user!	No user logged on.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	60	
MAIN_TEXTS	T342	Logging on!	The phone is trying logon with a user.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T342b	Logging on!	The phone is trying logon with a user.	DBC444	DBC444	2	16 Bold	25	258	
MAIN_TEXTS	T342c	Logging on!	The phone is trying logon with a user.	DBC446	DBC446	1	24 Bold	30	466	
MAIN_TEXTS	T343	Your connection to \rthe world.	The welcome page, do not translate this sentence.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	TRUE
MAIN_TEXTS	T344	Details:	See the detail of the number.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	70	
MAIN_TEXTS	T345	Edit:	Edit the number.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	10	70	
MAIN_TEXTS	T346	Delete:	Delete the number.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	10	70	
MAIN_TEXTS	T347	Add new manual input	Add the number to contacts manually.	DBC43x DBC446, DBC43x, DBC444	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T348	Add new from Call List	Add the number to contacts from Call list.	DBC43x	DBC43x	1	8 Reg.	25	120	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T348b	Add new from Call List	Add the number to contacts from Call list.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T348c	Add new from Call List	Add the number to contacts from Call list.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T349	Delete all contacts	Delete all the contacts in the contacts.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T349b	Delete all contacts	Delete all the contacts in the contacts.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T349c	Delete all contacts	Delete all the contacts in the contacts.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T350	Exit Contacts	Exit the contacts page.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T350b	Exit Contacts	Exit the contacts page.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T350c	Exit Contacts	Exit the contacts page.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T351	Exit Edit	Exit the edit page.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T351b	Exit Edit	Exit the edit page.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T351c	Exit Edit	Exit the edit page.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T352	Contacts empty!	No contact in the contacts.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T352b	Contacts empty!	No contact in the contacts.	DBC444	DBC444	3	16 Bold	30	253	
MAIN_TEXTS	T352c	Contacts empty!	No contact in the contacts.	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T354	Exit Add new	Exit the edit page.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T354b	Exit Add new	Exit the edit page.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T354c	Exit Add new	Exit the edit page.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T355	Exit Edit Name	Exit the edit page.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T356	Exit Edit Number	Exit the edit page.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T357	Exit Edit Ring	Exit the edit page.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T358	Set Ring signal to:	The confirmation of the ring signal settings for special contact.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T358b	Set Ring signal to:	The confirmation of the ring signal settings for special contact.	DBC444	DBC444, DBC446	2	16 Bold	30	253	
MAIN_TEXTS	T359	Cannot be undone!	Warning message for settings not possible.	DBC43x		1	8 Reg.	25	128	
MAIN_TEXTS	T360	Free on busy	Show if Free on Busy is enabled/disabled.	DBC43x	DBC43x	1	8 Reg.	20	80	
MAIN_TEXTS	T360b	Free on busy	Show if Free on Busy is enabled/disabled.	DBC444	DBC444	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T360c	Free on busy	Show if Free on Busy is enabled/disabled.	DBC446	DBC446	1	18 Reg.	30	300	
MAIN_TEXTS	T361	My Presence	Show my presence menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T361b	My Presence	Show my presence menu.	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T361c	My Presence	Show my presence menu.	DBC446	DBC446	1	18 Reg.	40	463	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T362	Exit My Presence	Exit My Presence.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T363	Match in Contacts!	The same name exists already in the Contacts.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T363b	Match in Contacts!	The same name exists already in the Contacts.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T363c	Match in Contacts!	The same name exists already in the Contacts.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T364	Duplicate?	Ask if need to duplicate the contact.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T364b	Duplicate?	Ask if need to duplicate the contact.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T364c	Duplicate?	Ask if need to duplicate the contact.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T365	Exit Lunch	Exit absence reason Lunch.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T366	Disable all diversions	Cancel all diversions.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T366b	Disable all diversions	Cancel all diversions.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T366c	Disable all diversions	Cancel all diversions.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T367	Log off:	Log of the user.	DBC43x	DBC43x	1	8 Reg.	15	60	
MAIN_TEXTS	T367b	Log off:	Log of the user.	DBC444	DBC444	1	16 Bold	15	120	
MAIN_TEXTS	T367c	Log off:	Log of the user.	DBC446	DBC446	1	14 Bold	20	230	
MAIN_TEXTS	T368	Log On Temporary User	Log On Temporary User.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T368b	Log On Temporary User	Log On Temporary User.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T368c	Log On Temporary User	Log On Temporary User.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T369	Cancel all Callbacks	Deactivate all Callbacks.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T369b	Cancel all Callbacks	Deactivate all Callbacks.	DBC444	DBC444	1	14 Bold	25	138	
MAIN_TEXTS	T369c	Cancel all Callbacks	Deactivate all Callbacks.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T370	Added to Contacts	Add the number to contacts.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T371	Exit Busy	Exit absence reason Busy.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T372	Exit Absent	Exit absence reasons.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T373	Exit Trip	Exit absence reason Trip.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T374	Exit Courses	Exit absence reason Courses.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T375	Exit Day Off	Exit absence reason Day Off.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T376	Exit Meeting	Exit absence reason Meeting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T377	Exit Illness	Exit absence reason Meeting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T378	Exit Vacation	Exit absence reason Meeting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T379	Exit Gone Home	Exit absence reason Meeting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T380	Exit My mobile phone	Show Exit my mobile menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T381	Contacts	Show contacts menu in Follow-me.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T381b	Contacts	Show contacts	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T381c	Contacts	Show contacts	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T382	Call List	Show Call list menu in Follow-me.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T382b	Call List	Show Call list	DBC444	DBC444	1	16 Bold	25	270	
MAIN_TEXTS	T382c	Call List	Show Call list	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T385	Shortcut:	Shortcut the phone number.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T385b	Shortcut:	Shortcut the phone number.	DBC444	DBC444, DBC446	2	16 Bold	25	253	
MAIN_TEXTS	T386	Shortcuts	Show Shortcuts menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T386b	Shortcuts	Show Shortcuts menu.	DBC444	DBC444	1	16 Bold	20	150	
MAIN_TEXTS	T386c	Shortcuts	Show Shortcuts menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T388	Delete	Show Delete Shortcuts menu.	DBC43x	DBC43x	1	8 Reg.	25	70	
MAIN_TEXTS	T388b	Delete	Show Delete Shortcuts menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T388c	Delete	Show Delete Shortcuts menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T391	Delete all Shortcuts	Show Delete all Shortcuts menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T391b	Delete all Shortcuts	Show Delete all Shortcuts menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T391c	Delete all Shortcuts	Show Delete all Shortcuts menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T392	Exit My Availability	Show Exit My Availability menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T392b	Exit My Availability	Show Exit My Availability menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T392c	Exit My Availability	Show Exit My Availability menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T393	Exit Follow-me	Show Exit Follow-me menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T393b	Exit Follow-me	Show Exit Follow-me menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T393c	Exit Follow-me	Show Exit Follow-me menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T396	Deactivate Follow-me	Show Deactivate Follow-me menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T396b	Deactivate Follow-me	Show Deactivate Follow-me menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T396c	Deactivate Follow-me	Show Deactivate Follow-me menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T397	Set Follow-me to	The confirmation of Follow me.	DBC43x	DBC43x	1	8 Reg.	25	128	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T397b	Set Follow-me to	The confirmation of Follow me.	DBC444	DBC444	1	16 Bold	25	268	
MAIN_TEXTS	T397c	Set Follow-me to	The confirmation of Follow me.	DBC446	DBC446	1	18 Reg.	40	480	
MAIN_TEXTS	T399	Phone Contrast	Show Phone Contrast menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T399b	Phone Contrast	Show Phone Contrast menu.	DBC444	DBC444	1	16 Bold	25	296	
MAIN_TEXTS	T399c	Phone Contrast	Show Phone Contrast menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T400	ON	Turn on Free-on-busy.	DBC43x	DBC43x	1	8 Reg.	6	32	
MAIN_TEXTS	T400b	ON	Turn on Free-on-busy.	DBC444	DBC444	1	16 Bold	6	48	
MAIN_TEXTS	T400c	ON	Turn on Free-on-busy.	DBC446	DBC446	1	18 Reg.	6	100	
MAIN_TEXTS	T401	OFF	Turn off Free-on-busy.	DBC43x	DBC43x	1	8 Reg.	6	32	
MAIN_TEXTS	T401b	OFF	Turn off Free-on-busy.	DBC444	DBC444	1	16 Bold	6	48	
MAIN_TEXTS	T401c	OFF	Turn off Free-on-busy.	DBC446	DBC446	1	18 Reg.	6	100	
MAIN_TEXTS	T402	, send busy on busy	Indication of turn off Free-on-busy.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T402b	, send busy on busy	Indication of turn off Free-on-busy.	DBC444	DBC444	1	16 Bold	25	220	
MAIN_TEXTS	T402c	, send busy on busy	Indication of turn off Free-on-busy.	DBC446	DBC446	1	14 Bold	30	300	
MAIN_TEXTS	T403	, put call through	Indication of turn on Free-on-busy.	DBC43x	DBC43x	1	8 Reg.	25	90	
MAIN_TEXTS	T403b	, put call through	Indication of turn on Free-on-busy.	DBC444	DBC444	1	16 Bold	25	220	
MAIN_TEXTS	T403c	, put call through	Indication of turn on Free-on-busy.	DBC446	DBC446	1	14 Bold	30	300	
MAIN_TEXTS	T404	Set Free on busy to:	Confirmation of Free on Busy.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T406	Exit Default Ring Signal	Show Exit Default Ring Signal menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T409	Exit Settings	Show Exit Settings menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T409b	Exit Settings	Show Exit Settings menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T409c	Exit Settings	Show Exit Settings menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T410	Security and Access	Show Security and Access menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T410b	Security and Access	Show Security and Access menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T410c	Security and Access	Show Security and Access menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T411	Administrator	Show Admin Settings menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T411b	Administrator	Show Admin Settings menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T411c	Administrator	Show Admin Settings menu.	DBC446	DBC446	1	18 Reg.	40	480	
MAIN_TEXTS	T412	Data:	Data input field of Shortcut.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	10	70	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T414	Label:	Label input field of Shortcut.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	10	70	
MAIN_TEXTS	T416	Exit Shortcuts	Show Exit Shortcuts menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T416b	Exit Shortcuts	Show Exit Shortcuts menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T416c	Exit Shortcuts	Show Exit Shortcuts menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T417	Select a Shortcut by pressing the key!	Notice information for Shortcuts. Use multi-row here.	DBC43x	DBC43x	1	8 Reg.	50	256	
MAIN_TEXTS	T417b	Select a Shortcut by pressing the key!	Notice information for Shortcuts. Use multi-row here.	DBC444	DBC444, DBC446	2	16 Bold	50	143	
MAIN_TEXTS	T420	by System administrator	Show "by System administrator" on the display.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T421	Saved data and label!	Show "Saved data and label!" on the display.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T422	Edit Data	Show Edit Data menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T423	Edit Label	Show Edit Data menu. BC43x	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T424	Delete Shortcut(s)?	Show Delete Short-cut(s)menu.	DBC43x	DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T424b	Delete Shortcut(s)?	Show Delete Short-cut(s)menu.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T425	Not programmed!	Show "Not programmed!" on the display.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T425b	Not programmed!	Show "Not programmed!" on the display.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T425c	Not programmed!	Show "Not programmed!" on the display.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T426	Program shortcut?	Show "Program shortcut?" on the display.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T426b	Program shortcut?	Show "Program shortcut?" on the display.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T426c	Program shortcut?	Show "Program shortcut?" on the display.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T427	Reprogram the key?	Show "Reprogram the key?" on the display.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T427b	Reprogram the key?	Show "Reprogram the key?" on the display.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T427c	Reprogram the key?	Show "Reprogram the key?" on the display.	DBC446	DBC446	1	18 Reg.	30	253	
MAIN_TEXTS	T428	Add new from Contacts	Show the Add in select list.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T428b	Add new from Contacts	Show the Add in select list.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T428c	Add new from Contacts	Show the Add in select list.	DBC446	DBC446	1	18 Reg.	40	468	
MAIN_TEXTS	T429	Phone	Show phone model	DBC43x	DBC43x	1	8 Reg.	15	40	
MAIN_TEXTS	T429b	Phone	Show phone model	DBC444	DBC444	1	16 Bold	15	80	
MAIN_TEXTS	T429c	Phone	Show phone model	DBC446	DBC446	1	18 Reg.	15	150	
MAIN_TEXTS	T430	Current log on PIN!	Show the menu of Current log on PIN!	DBC43x	DBC43x	1	8 Reg.	35	128	
MAIN_TEXTS	T430b	Current log on PIN!	Show the menu of Current log on PIN!	DBC444	DBC444	1	16 Bold	35	220	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T430c	Current log on PIN!	Show the menu of Current log on PIN!	DBC446	DBC446	1	14 Reg.	35	220	
MAIN_TEXTS	T431	New PIN (less than 7digits)!	Show the menu of New PIN(less than 7 digits)!	DBC43x	DBC43x	1	8 Reg.	35	128	
MAIN_TEXTS	T431b	New PIN (less than 7digits)!	Show the menu of New PIN(less than 7 digits)!	DBC444	DBC444	1	16 Bold	35	220	
MAIN_TEXTS	T431c	New PIN (less than 7digits)!	Show the menu of New PIN(less than 7 digits)!	DBC446	DBC446	1	14 Reg.	35	220	
MAIN_TEXTS	T432	Confirm PIN (less than 7digits)!	The confirmation page of the new PIN.	DBC43x	DBC43x	1	8 Reg.	35	128	
MAIN_TEXTS	T432b	Confirm PIN (less than 7digits)!	The confirmation page of the new PIN.	DBC444	DBC444	1	16 Bold	35	220	
MAIN_TEXTS	T432c	Confirm PIN (less than 7digits)!	The confirmation page of the new PIN.	DBC446	DBC446	1	14 Reg.	35	220	
MAIN_TEXTS	T433	PIN:	Input field of PIN.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	6	32	
MAIN_TEXTS	T434	Wrong PIN	Indication of Wrong PIN.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T434b	Wrong PIN	Indication of Wrong PIN.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T434c	Wrong PIN	Indication of Wrong PIN.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T435	Please check and retry!	Indication of Wrong PIN.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T435b	Please check and retry!	Indication of Wrong PIN.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T435c	Please check and retry!	Indication of Wrong PIN.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T436	Exit Change PIN	Show Exit Change PIN menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T439	PIN length error!	Indication of error in PIN length.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T439b	PIN length error!	Indication of error in PIN length.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T439c	PIN length error!	Indication of error in PIN length.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T440	Handset	Indication of Handset is in use.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T440b	Handset	Indication of Handset is in use.	DBC444	DBC444, DBC446	1	16 Bold	15	178	
MAIN_TEXTS	T441	Speaker	Indication of Speaker is in use.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T441b	Speaker	Indication of Speaker is in use.	DBC444	DBC444, DBC446	1	16 Bold	15	178	
MAIN_TEXTS	T442	Clear:	Clear a call when multi-calls are using.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T442b	Clear:	Clear a call when multi-calls are using.	DBC444	DBC444	1	16 Bold	15	100	
MAIN_TEXTS	T442c	Clear:	Clear a call when multi-calls are using.	DBC446	DBC446	1	14 Bold	25	150	
MAIN_TEXTS	T443	Conference	Make the multi-call to a conference.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T443b	Conference	Label of the Conference key	DBC444	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T444	Transfer to:	Transfer a call to another phone.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T444b	Transfer to:	Transfer a call to another phone.	DBC444	DBC444	1	16 Bold	15	100	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T444c	Transfer to:	Transfer a call to another phone.	DBC446	DBC446	1	14 Bold	25	150	
MAIN_TEXTS	T445	Retrieve:	Retrieve a call from hold.	DBC43x	DBC43x	1	8 Reg.	15	70	
MAIN_TEXTS	T445b	Retrieve:	Retrieve a call from hold.	DBC444	DBC444	1	16 Bold	15	100	
MAIN_TEXTS	T445c	Retrieve:	Retrieve a call from hold.	DBC446	DBC446	1	14 Bold	25	150	
MAIN_TEXTS	T446	Exit Special	Show Exit Special menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T447	Exit Official Matter	Show Exit Official Matter menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T448	Exit Free Time	Show Exit Free Time menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T449	Exit Parental Leave	Show Exit Parental Leave menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T450	Failed Authentication!	Indication page of Failed Authentication.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T450b	Failed Authentication!	Indication page of Failed Authentication.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T450c	Failed Authentication!	Indication page of Failed Authentication.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T451	Check password!	Indication page of Failed Authentication.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T451b	Check password!	Indication page of Failed Authentication.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T451c	Check password!	Indication page of Failed Authentication.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T452	Passed Admin User	Indication page of Passed Authentication.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T452b	Passed Admin User	Indication page of Passed Authentication.	DBC444	DBC444	1	16 Bold	25	178	
MAIN_TEXTS	T452c	Passed Admin User	Indication page of Passed Authentication.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T453	Authentication!	Indication page of Passed Authentication.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T453b	Authentication!	Indication page of Passed Authentication.	DBC444	DBC444	1	16 Bold	25	178	
MAIN_TEXTS	T453c	Authentication!	Indication page of Passed Authentication.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T454	Log off Administrator	Show Log off Admin in the select list.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T454b	Log off Administrator	Show Log off Admin in the select list.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T454c	Log off Administrator	Show Log off Admin in the select list.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T455	User	Show the User menu.	DBC43x	DBC43x	1	8 Reg.	10	40	
MAIN_TEXTS	T455b	User	Show the User menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T455c	User	Show the User menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T456	Free User	Free User selection. The user is allowed to log on/off.	DBC43x	DBC43x	1	8 Reg.	20	80	
MAIN_TEXTS	T456b	Free User	Free User selection. The user is allowed to log on/off.	DBC444	DBC444	1	16 Bold	30	275	
MAIN_TEXTS	T456c	Free User	Free User selection. The user is allowed to log on/off.	DBC446	DBC446	1	14 Bold	40	443	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T457	Temporary User	Show the Temp. User menu.	DBC43x	DBC43x	1	8 Reg.	20	80	
MAIN_TEXTS	T457b	Temporary User	Show the Temp. User menu.	DBC44	DBC44	1	16 Bold	30	275	
MAIN_TEXTS	T457c	Temporary User	Show the Temp. User menu.	DBC46	DBC46	1	14 Bold	40	443	
MAIN_TEXTS	T458	Permanent User	Show the Permanent User menu.	DBC43x	DBC43x	1	8 Reg.	20	80	
MAIN_TEXTS	T458b	Permanent User	Show the Permanent User menu.	DBC44	DBC44	1	16 Bold	30	275	
MAIN_TEXTS	T458c	Permanent User	Show the Permanent User menu.	DBC46	DBC46	1	14 Bold	40	443	
MAIN_TEXTS	T459	Default (Latin)	Show the Default input Key pad.	DBC43x	DBC43x	1	8 Reg.	20	80	
MAIN_TEXTS	T459b	Default (Latin)	Show the Default input Key pad.	DBC44	DBC44	1	16 Bold	30	275	
MAIN_TEXTS	T459c	Default (Latin)	Show the Default input Key pad.	DBC46	DBC46	1	14 Bold	40	443	
MAIN_TEXTS	T460	Cleared	Indication of the Cleared incoming call.	DBC43x	DBC43x	1	8 Reg.	15	32	
MAIN_TEXTS	T460b	Cleared	Indication of the Cleared incoming call.	DBC44	DBC44, DBC46	1	16 Bold	15	253	
MAIN_TEXTS	T461	Duration	Indication of the duration of the call.	DBC43x	DBC43x	1	8 Reg.	15	32	
MAIN_TEXTS	T461b	Duration	Indication of the duration of the call.	DBC44	DBC44, DBC46	1	16 Bold	15	253	
MAIN_TEXTS	T462	Failed User Log on!	Indication of logon failure.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T462b	Failed User Log on!	Indication of logon failure.	DBC44	DBC44	2	16 Bold	30	253	
MAIN_TEXTS	T462c	Failed User Log on!	Indication of logon failure.	DBC46	DBC46	1	18 Bold	40	466	
MAIN_TEXTS	T463	No calls	Indication of No calls in the log on page.	DBC43x	DBC43x	1	8 Reg.	15	60	
MAIN_TEXTS	T463b	No calls	Indication of No calls in the log on page.	DBC44	DBC44	1	16 Bold	15	253	
MAIN_TEXTS	T463c	No calls	Indication of No calls in the log on page.	DBC46	DBC46	1	18 Bold	40	466	
MAIN_TEXTS	T464	Handsfree preset mode!	Indication of Handsfree preset mode.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T464b	Handsfree preset mode!	Indication of Handsfree preset mode.	DBC44	DBC44, DBC46	2	16 Bold	30	178	
MAIN_TEXTS	T465	Headset preset mode!	Indication of Headset preset mode.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T465b	Headset preset mode!	Indication of Headset preset mode.	DBC44	DBC44, DBC46	2	16 Bold	30	178	
MAIN_TEXTS	T466	Loudspeaking mode!	Indication of Loudspeaking mode.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T466b	Loudspeaking mode!	Indication of Loudspeaking mode.	DBC44	DBC44, DBC46	2	16 Bold	30	178	
MAIN_TEXTS	T467	Handsfree mode!	Indication of Handsfree mode!	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T467b	Handsfree mode!	Indication of Handsfree mode!	DBC44	DBC44, DBC46	2	16 Bold	30	178	
MAIN_TEXTS	T468	Handsfree not supported!	Indication of Handfree not supported.	DBC43x	DBC46, DBC43x, DBC44	1	8 Reg.	25	128	
MAIN_TEXTS	T469	Pick up Handset to talk!	Indication of Pick up Handset to talk.	DBC43x	DBC46, DBC43x, DBC44	1	8 Reg.	25	128	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T470	Shut down the phone?	Ask if shut down the phone.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T470b	Shut down the phone?	Ask if shut down the phone.	DBC44	DBC44, DBC446	1	16 Bold	30	240	
MAIN_TEXTS	T471	Restart the phone?	Ask if the user wants to restart the telephone.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T471b	Restart the phone?	Ask if the user wants to restart the telephone.	DBC44	DBC44	1	16 Bold	30	240	
MAIN_TEXTS	T471c	Restart the phone?	Ask if the user wants to restart the telephone.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T472	Shutting down...	Indication of the phone is shutting down.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T472b	Shutting down...	Indication of the phone is shutting down.	DBC44	DBC44, DBC446	1	16 Bold	30	258	
MAIN_TEXTS	T473	Transfer to My mobile	Show the transfer notice.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T473b	Transfer to My mobile	Show the transfer notice.	DBC44	DBC44	1	16 Bold	30	240	
MAIN_TEXTS	T473c	Transfer to My mobile	Show the transfer notice.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T474	Transfer to Operator	Show the transfer notice.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T474b	Transfer to Operator	Show the transfer notice.	DBC44	DBC44	1	16 Bold	30	240	
MAIN_TEXTS	T474c	Transfer to Operator	Show the transfer notice.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T475	Callbacks are pending	Indicate that Callbacks are pending.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T475b	Callbacks are pending	Indicate that Callbacks are pending.	DBC44	DBC44	2	16 Bold	30	253	
MAIN_TEXTS	T475c	Callbacks are pending	Indicate that Callbacks are pending.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T476	Delete all?	Ask if Delete all the callbacks.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T476b	Delete all?	Ask if Delete all the callbacks.	DBC44	DBC44	2	16 Bold	30	253	
MAIN_TEXTS	T476c	Delete all?	Ask if Delete all the callbacks.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T477	Shortcut(s) deleted!	Indication of Shortcut deleted.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	128	
MAIN_TEXTS	T479	Delete Shortcuts?	Indication of All Shortcuts deleted.	DBC44	DBC44	2	16 Bold	30	253	
MAIN_TEXTS	T479b	Delete Shortcuts?	Indication of All Shortcuts deleted.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T479c	Delete Shortcuts?	Indication of All Shortcuts deleted.	DBC446	DBC446	1	18 Reg.	35	330	
MAIN_TEXTS	T480	Software	Show the Software info menu.	DBC43x	DBC43x	1	8 Reg.	10	70	
MAIN_TEXTS	T480b	Software	Show the Software info menu.	DBC44	DBC44	1	16 Bold	20	148	
MAIN_TEXTS	T480c	Software	Show the Software info menu.	DBC446	DBC446	1	18 Reg.	35	230	
MAIN_TEXTS	T481	Phone IP Address...	Show the Phone IP Address info menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T481b	Phone IP Address...	Show the Phone IP Address info menu.	DBC44	DBC44	1	16 Bold	30	275	
MAIN_TEXTS	T481c	Phone IP Address...	Show the Phone IP Address info menu.	DBC446	DBC446	1	18 Reg.	40	463	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T482	Phone Web Address...	Show the Phone Web Address info menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T482b	Phone Web Address...	Show the Phone Web Address info menu.	DBC44	DBC44	1	16 Bold	30	275	
MAIN_TEXTS	T482c	Phone Web Address...	Show the Phone Web Address info menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T483	Help	Show the Help info menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T483b	Help	Show the Help info menu.	DBC44	DBC44	1	16 Bold	30	270	
MAIN_TEXTS	T483c	Help	Show the Help info menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T484	About:	Show the phone type.	DBC43x	DBC43x	1	8 Reg.	10	32	
MAIN_TEXTS	T484b	About:	Show the phone type.	DBC44	DBC44	1	16 Bold	10	80	
MAIN_TEXTS	T484c	About:	Show the phone type.	DBC446	DBC446	1	18 Reg.	35	230	
MAIN_TEXTS	T485	Exit Edit Label	Show Exit Edit Label menu.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	120	
MAIN_TEXTS	T486	Exit Edit Data	Show Exit Edit Data menu.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	120	
MAIN_TEXTS	T487	Callback	Show current programmable key as Callback.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T487b	Callback	Show current programmable key as Callback.	DBC44	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T488	Call Pick-Up	Show current programmable key as Call Pick-Up.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T488b	Call Pick-Up	Show current programmable key as Call Pick-Up.	DBC44	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T489	Call Waiting	Show current programmable key as Call Waiting.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T489b	Call Waiting	Show current programmable key as Call Waiting.	DBC44	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T490	Intrusion	Show current programmable key as Intrusion.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T490b	Intrusion	Show current programmable key as Intrusion.	DBC44	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T491	Home address	Show current programmable key as Home address.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T491b	Home address	Show current programmable key as Home address.	DBC44	DBC444, DBC446	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T496	All Shortcuts deleted!	Show "All Shortcuts deleted!" in display.	DBC43x	DBC446, DBC43x, DBC44	1	8 Reg.	25	128	
MAIN_TEXTS	T497	Check Network cable!	Show "Check Network cable!" in display.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T497b	Check Network cable!	Show "Check Network cable!" in display.	DBC44	DBC444	1	16 Bold	30	258	
MAIN_TEXTS	T497c	Check Network cable!	Show "Check Network cable!" in display.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T498	Logged Off!	Show "Logged Off!" in display when shut down the phone.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T498b	Logged Off!	Show "Logged Off!" in display when shut down the phone.	DBC44	DBC444	1	16 Bold	30	258	
MAIN_TEXTS	T498c	Logged Off!	Show "Logged Off!" in display when shut down the phone.	DBC446	DBC446	1	18 Bold	40	466	
MAIN_TEXTS	T499	Shut down the phone and PC network connection?	The confirmation page for the shut down functionality.	DBC43x	DBC43x	1	8 Reg.	50	256	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T499b	Shut down the phone and PC network connection?	The confirmation page for the shut down functionality.	DBC444	DBC444, DBC446	2	16 Bold	60	253	
MAIN_TEXTS	T501	* for Power up	Show button for Power up. * is locally replaced with the power icon.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T501b	* for Power up	Show button for Power up. * is locally replaced with the power icon.	DBC444	DBC444, DBC446	1	16 Bold	30	242	
MAIN_TEXTS	T502	Time:	Show the current time.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	10	32	
MAIN_TEXTS	T503	Date:	Show the current date.	DBC43x	DBC43x	1	8 Reg.	10	32	
MAIN_TEXTS	T503b	Date:	Show the current date.	DBC444	DBC444	1	16 Bold	10	80	
MAIN_TEXTS	T503c	Date:	Show the current date.	DBC446	DBC446	1	18 Reg.	35	230	
MAIN_TEXTS	T504	Monitor:	Monitor key.	DBC43x	DBC43x	1	8 Reg.	15	60	
MAIN_TEXTS	T504b	Monitor:	Monitor key.	DBC444	DBC444	1	16 Bold	15	100	
MAIN_TEXTS	T504c	Monitor:	Monitor key.	DBC446	DBC446	1	14 Reg.	20	150	
MAIN_TEXTS	T505	Alert	Show the Alert menu.	DBC43x	DBC43x	1	8 Reg.	10	32	
MAIN_TEXTS	T505b	Alert	Show the Alert menu.	DBC444	DBC444	1	16 Bold	10	50	
MAIN_TEXTS	T505c	Alert	Show the Alert menu.	DBC446	DBC446	1	18 Reg.	20	150	
MAIN_TEXTS	T506	Edit Alert	Show the Edit Alert menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T506b	Edit Alert	Show the Edit Alert menu.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T506c	Edit Alert	Show the Edit Alert menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T507	Exit Edit Alert	Show the Exit Alert menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T508	Set Alert to:	Confirmation of Alert setting.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T509	Visual only	Show Visual only menu.	DBC43x	DBC43x	1	8 Reg.	20	70	
MAIN_TEXTS	T509b	Visual only	Show Visual only menu.	DBC444	DBC444	1	16 Bold	20	150	
MAIN_TEXTS	T509c	Visual only	Show Visual only menu.	DBC446	DBC446	1	18 Reg.	30	261	
MAIN_TEXTS	T510	Conference All	Include all active calls into a conference.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T510b	Conference All	Include all active calls into a conference.	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T510c	Conference All	Include all active calls into a conference.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T511	My VoiceMail	Show My VoiceMail menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T511b	My VoiceMail	Show My VoiceMail menu.	DBC444	DBC444	1	16 Bold	30	296	
MAIN_TEXTS	T511c	My VoiceMail	Show My VoiceMail menu.	DBC446	DBC446	1	18 Reg.	40	423	
MAIN_TEXTS	T512	My Messages	Show My Messages menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T512b	My Messages	Show My Messages menu.	DBC444	DBC444	1	16 Bold	30	296	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T512c	My Messages	Show My Messages menu.	DBC446	DBC446	1	18 Reg.	40	423	
MAIN_TEXTS	T513	Edit VoiceMail number	Show Edit VoiceMail number in more list.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T514	Edit Messages number	Show Edit Message number in more list.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T515	New number:	New number input field.	DBC43x	DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T515b	New number:	New number input field.	DBC446	DBC446	1	18 Reg.	30	220	
MAIN_TEXTS	T516	Exit Edit VoiceMail	Show Exit Edit VoiceMail menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T517	Exit Edit Messages	Show Edit Messages menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T518	Delete & Exit Messages	Show Delete & Exit Messages menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T519	Exit Messages	Show Exit Messages menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T520	New from:	New message from...	DBC43x	DBC43x, DBC444	1	8 Reg.	20	70	
MAIN_TEXTS	T521	Program Voice Mail?	Show Program Voie Mail?	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T521b	Program Voice Mail?	Show Program Voie Mail?	DBC444	DBC444, DBC446	1	16 Bold	30	253	
MAIN_TEXTS	T522	Program Messages?	Show Program Message?	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T522b	Program Messages?	Show Program Message?	DBC444	DBC444, DBC446	1	16 Bold	30	253	
MAIN_TEXTS	T523	Transfering...	Show Transfering... in display.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T524	Panel	Show the Panel word.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	10	40	
MAIN_TEXTS	T525	Alert 1st call	Show Alert 1st call menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T525b	Alert 1st call	Show Alert 1st call menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T525c	Alert 1st call	Show Alert 1st call menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T526	Alert 2nd and 3rd call	Show Alert 2nd and 3rd call menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T526b	Alert 2nd and 3rd call	Show Alert 2nd and 3rd call menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T526c	Alert 2nd and 3rd call	Show Alert 2nd and 3rd call menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T527	Add new	Show Add new menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	70	
MAIN_TEXTS	T528	Exit Alert	Show Exit Alert menu.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T529	Auto Answer	Show Auto Answer menu.	DBC43x	DBC43x	1	8 Reg.	25	70	
MAIN_TEXTS	T529b	Auto Answer	Show Auto Answer menu.	DBC444	DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T529c	Auto Answer	Show Auto Answer menu.	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T530	Auto Answer Off	Show Auto Answer Off menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T530b	Auto Answer Off	Show Auto Answer Off menu.	DBC444	DBC444	1	16 Bold	30	275	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T530c	Auto Answer Off	Show Auto Answer Off menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T531	Auto Answer On	Show Auto Answer On menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T531b	Auto Answer On	Show Auto Answer On menu.	DBC444	DBC444	1	16 Bold	30	275	
MAIN_TEXTS	T531c	Auto Answer On	Show Auto Answer On menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T532	Delayed Auto Answer	Show Delayed Auto Answer menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T532b	Delayed Auto Answer	Show Delayed Auto Answer menu.	DBC444	DBC444	1	16 Bold	30	275	
MAIN_TEXTS	T532c	Delayed Auto Answer	Show Delayed Auto Answer menu.	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T533	Saved		DBC446, DBC43x, DBC444	DBC43x	1	8 Reg.	25	70	
MAIN_TEXTS	T534	VLAN ID range (1-4094)	Indication input of VLANID.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T534b	VLAN ID range (1-4094)	Indication input of VLANID.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T534c	VLAN ID range (1-4094)	Indication input of VLANID.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T535	Please check your input!	Error message of wrong input of VLAN ID.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T535b	Please check your input!	Error message of wrong input of VLAN ID.	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T535c	Please check your input!	Error message of wrong input of VLAN ID.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T536	DPU1 Contrast	Show DPU1 contrast menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T536b	DPU1 Contrast	Show DPU1 contrast menu.	DBC444	DBC444, DBC446	1	16 Bold	30	270	
MAIN_TEXTS	T537	DPU1 Brightness	Show DPU1 brightness menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T537b	DPU1 Brightness	Show DPU1 brightness menu.	DBC444	DBC444, DBC446 DBC446, DBC43x, DBC444	1	16 Bold	30	270	
MAIN_TEXTS	T538	Set DPU Contrast?	Confirmation of DPU contrast.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T539	Set DPU Brightness?	Confirmation of DPU brightness.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	128	
MAIN_TEXTS	T540	KPU	Show KPU info menu.	DBC43x	DBC43x	1	8 Reg.	5	32	
MAIN_TEXTS	T540b	KPU	Show KPU info menu.	DBC444	DBC444, DBC446	1	16 Bold	5	60	
MAIN_TEXTS	T541	DPU	Show DPU info menu.	DBC43x	DBC43x	1	8 Reg.	5	32	
MAIN_TEXTS	T541b	DPU	Show DPU info menu.	DBC444	DBC444, DBC446	1	16 Bold	5	60	
MAIN_TEXTS	T542	Delayed	Indicate some delayed issues, e.g. Delayed Auto Answer.	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	10	40	
MAIN_TEXTS	T543	Transfer	Show Transfer in the display.	DBC43x	DBC43x	1	8 Reg.	10	40	
MAIN_TEXTS	T543b	Transfer	Label of the Transfer key	DBC444	DBC444, DBC446	2	14 Bold, Cond.	10	66	
MAIN_TEXTS	T544	Delete all contacts?	Ask if delete all contacts.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T544b	Delete all contacts?	Ask if delete all contacts.	DBC444	DBC444	3	16 Bold	30	253	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T544c	Delete all contacts?	Ask if delete all contacts.	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T545	DPU2 Contrast	Show DPU2 contrast menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T545b	DPU2 Contrast	Show DPU2 contrast menu.	DBC444	DBC444, DBC446	1	16 Bold	30	270	
MAIN_TEXTS	T546	DPU2 Brightness	Show DPU2 brightness menu.	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T546b	DPU2 Brightness	Show DPU2 brightness menu.	DBC444	DBC444, DBC446	1	16 Bold	30	270	
MAIN_TEXTS	T547	Hold	Show Hold menu	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T548	Recording	Label of the recording key.	DBC444	DBC444	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T548b	Recording	Label of the recording key.	DBC43x	DBC43x	1	8 Reg.	20	128	
MAIN_TEXTS	T548c	Recording	Label of the recording key.	DBC446	DBC446	1	14 Reg.	25	200	
MAIN_TEXTS	T549	Personal Number	Indication of the Personal Number key	DBC444	DBC444	1	16 Bold	30	253	
MAIN_TEXTS	T549b	Personal Number	Indication of the Personal Number key	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T549c	Personal Number	Indication of the Personal Number key	DBC446	DBC446	1	18 Bold	40	476	
MAIN_TEXTS	T550	Add * to Contacts?	Confirm adding a new entry to Contacts from CorpDir. * is locally replaced by the name.	DBC444	DBC43x, DBC444	1	14 Bold	20	160	
MAIN_TEXTS	T550b	Add * to Contacts?	Confirm adding a new entry to Contacts from CorpDir. * is locally replaced by the name.	DBC446	DBC446	1	18 Bold	25	230	
MAIN_TEXTS	T551	PEN:	Label of the Personal Number key.	DBC444	DBC444	1	14 Bold	5	32	
MAIN_TEXTS	T551b	PEN:	Label of the Personal Number key.	DBC43x	DBC43x	1	8 Reg.	5	40	
MAIN_TEXTS	T551c	PEN:	Label of the Personal Number key.	DBC446	DBC446	1	14 Reg.	5	60	
MAIN_TEXTS	T552	Call started	Show call started time	DBC444	DBC43x, DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T552b	Call started	Show call started time	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T553	Call duration	Show call duration	DBC444	DBC43x, DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T553b	Call duration	Show call duration	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T554	Type of call	Show type of the call	DBC444	DBC43x, DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T554b	Type of call	Show type of the call	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T555	Call recorded	Show whether the call was recorded	DBC444	DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T555b	Call recorded	Show whether the call was recorded	DBC446	DBC446	1	18 Reg.	25	300	
MAIN_TEXTS	T556	Details	Details menu item	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T556b	Details	Details menu item	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T556c	Details	Details menu item	DBC446	DBC446	1	18 Reg.	30	463	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T557	Add to Shortcuts	The title of adding to Shortcuts	DBC444	DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T557b	Add to Shortcuts	The title of adding to Shortcuts	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T557c	Add to Shortcuts	The title of adding to Shortcuts	DBC446	DBC446	1	18 Reg.	40	253	
MAIN_TEXTS	T558	Set External Follow-me to	Show sub-title Set External Follow-me to	DBC444	DBC444	1	16 Bold	30	268	
MAIN_TEXTS	T558b	Set External Follow-me to	Show sub-title Set External Follow-me to	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T558c	Set External Follow-me to	Show sub-title Set External Follow-me to	DBC446	DBC446	1	18 Reg.	40	480	
MAIN_TEXTS	T561	Melody	Show Melody type and/or name	DBC444	DBC444	1	16 Bold	10	80	
MAIN_TEXTS	T561b	Melody	Show Melody type and/or name	DBC43x	DBC43x	1	8 Reg.	10	50	
MAIN_TEXTS	T561c	Melody	Show Melody type and/or name	DBC446	DBC446	1	14 Bold	10	100	
MAIN_TEXTS	T562	empty	Melody name empty	DBC444	DBC444	1	16 Bold	10	80	
MAIN_TEXTS	T562b	empty	Melody name empty	DBC43x	DBC43x	1	8 Reg.	10	60	
MAIN_TEXTS	T562c	empty	Melody name empty	DBC446	DBC446	1	18 Reg.	15	120	
MAIN_TEXTS	T563	** Missed calls	Show number of missed call in Idle state. ** is locally replaced by the number of missed calls and can be anywhere in the text.	DBC444	DBC446, DBC43x, DBC444	1	14 Bold	25	138	
MAIN_TEXTS	T564	Intensity	Show backlight intensity	DBC444	DBC446, DBC43x, DBC444	1	16 Bold	30	284	
MAIN_TEXTS	T565	My VoiceMail number	Enter My VoiceMail number	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T566	My Message number	Enter My Message number	DBC444	DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T567	Page	Show virtual page number	DBC444	DBC43x, DBC444	1	16 Bold	6	40	
MAIN_TEXTS	T567b	Page	Show virtual page number	DBC446	DBC446	1	18 Reg.	10	90	
MAIN_TEXTS	T568	Key	Show the key number	DBC444	DBC43x, DBC444	1	16 Bold	10	80	
MAIN_TEXTS	T568b	Key	Show the key number	DBC446	DBC446	1	18 Reg.	10	90	
MAIN_TEXTS	T569	Programmed by System administrator	Prompt that the key is programmed by system administrator	DBC444	DBC444	2	16 Bold	30	253	
MAIN_TEXTS	T569b	Programmed by System administrator	Prompt that the key is programmed by system administrator	DBC446	DBC446, DBC43x	1	18 Bold	40	476	
MAIN_TEXTS	T570	Edit Shortcuts	Edit Shortcuts	DBC444	DBC43x, DBC444	1	16 Bold	25	200	
MAIN_TEXTS	T570b	Edit Shortcuts	Edit Shortcuts	DBC446	DBC446	1	18 Reg.	30	253	
MAIN_TEXTS	T571	Exit Edit Shortcuts	Exit Edit Shortcuts menu	DBC444	DBC43x, DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T571b	Exit Edit Shortcuts	Exit Edit Shortcuts menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T575	Exit Details	Exit Details menu	DBC444	DBC43x, DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T575b	Exit Details	Exit Details menu	DBC446	DBC446	1	14 Bold	40	463	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T576	Corporate Directory can't be loaded!	Prompt that Corporate Directory can't be loaded!	DBC444	DBC444	3	16 Bold	50	253	
MAIN_TEXTS	T576b	Corporate Directory can't be loaded!	Prompt that Corporate Directory can't be loaded!	DBC43x	DBC43x	2	8 Reg.	50	128	
MAIN_TEXTS	T576c	Corporate Directory can't be loaded!	Prompt that Corporate Directory can't be loaded!	DBC446	DBC446	1	18 Bold	50	466	
MAIN_TEXTS	T577	Disable diversions	Show Disable diversions menu in Idle state	DBC444	DBC446, DBC43x, DBC444	1	14 Bold	25	138	
MAIN_TEXTS	T578	Set from Contacts	Set from Contacts menu	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T578b	Set from Contacts	Set from Contacts menu	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T578c	Set from Contacts	Set from Contacts menu	DBC446	DBC446	1	18 Reg.	40	463	
MAIN_TEXTS	T579	Exit set from Contacts	Exit set from Contacts menu	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T579b	Exit set from Contacts	Exit set from Contacts menu	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T579c	Exit set from Contacts	Exit set from Contacts menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T580	Exit External Follow-me	Exit External Follow-me menu	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T580b	Exit External Follow-me	Exit External Follow-me menu	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T580c	Exit External Follow-me	Exit External Follow-me menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T581	No received calls in CallList!	Prompt No received calls in CallList!	DBC444	DBC446, DBC43x, DBC444	3	16 Bold	50	253	
MAIN_TEXTS	T582	No dialed calls in CallList!	Prompt No dialed calls in CallList!	DBC444	DBC446, DBC43x, DBC444	3	16 Bold	50	253	
MAIN_TEXTS	T583	No missed calls in CallList!	Prompt No missed calls in CallList!	DBC444	DBC444	3	16 Bold	50	253	
MAIN_TEXTS	T583b	No missed calls in CallList!	Prompt No missed calls in CallList!	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T583c	No missed calls in CallList!	Prompt No missed calls in CallList!	DBC446	DBC446	1	18 Reg.	50	468	
MAIN_TEXTS	T584	Received	Show call type--Received call	DBC444	DBC43x, DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T584b	Received	Show call type--Received call	DBC446	DBC446	1	18 Reg.	20	160	
MAIN_TEXTS	T585	Dialed	Show call type--Dialed call	DBC444	DBC43x, DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T585b	Dialed	Show call type--Dialed call	DBC446	DBC446	1	18 Reg.	20	160	
MAIN_TEXTS	T586	** Missed	Show call type--Missed call. ** is locally replaced by the number of times that missing the call and can be anywhere in the text.	DBC444	DBC444	1	16 Bold	20	148	
MAIN_TEXTS	T586b	** Missed	Show call type--Missed call. ** is locally replaced by the number of times that missing the call and can be anywhere in the text.	DBC446	DBC446	1	18 Reg.	20	160	
MAIN_TEXTS	T587	Access code + number:	Enter the number External Follow-me to	DBC444	DBC43x, DBC444	1	16 Bold	30	220	
MAIN_TEXTS	T587b	Access code + number:	Enter the number External Follow-me to	DBC446	DBC446	1	14 Reg.	30	220	
MAIN_TEXTS	T588	Show all calls	Show all calls menu	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T588b	Show all calls	Show all calls menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T589	Show missed calls	Show missed calls menu	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T589b	Show missed calls	Show missed calls menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T590	Exit My Profile	Exit My Profile menu	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T591	Deactivate Profile	Deactivate Profile menu	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T592	Exit Melody	Exit Melody menu	DBC43x	DBC446, DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T593	Exit My Contacts	Exit My Contacts menu	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T593b	Exit My Contacts	Exit My Contacts menu	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T593c	Exit My Contacts	Exit My Contacts menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T594	Exit Corporate Directory	Exit Corporate Directory menu	DBC43x	DBC43x, DBC444	1	8 Reg.	25	120	
MAIN_TEXTS	T594b	Exit Corporate Directory	Exit Corporate Directory menu	DBC446	DBC446	1	14 Bold	40	463	
MAIN_TEXTS	T595	Corporat. Directory	Access to the corporate directory.	DBC444	DBC444	2	14 Bold, Cond.	20	66	
MAIN_TEXTS	T595b	Corporat. Directory	Access to the corporate directory.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T595c	Corporat. Directory	Access to the corporate directory.	DBC446	DBC446	1	14 Reg.	25	200	
MAIN_TEXTS	T596	My Contacts	My Contacts menu	DBC43x	DBC43x	1	8 Reg.	25	120	
MAIN_TEXTS	T596b	My Contacts	My Contacts menu	DBC444	DBC444	1	16 Bold	30	240	
MAIN_TEXTS	T596c	My Contacts	My Contacts menu	DBC446	DBC446	1	18 Reg.	40	300	
MAIN_TEXTS	T800	Time out!	Time out message.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T800b	Time out!	Time out message.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T800c	Time out!	Time out message.	DBC444	DBC444	1	14 Bold, Cond.	25	208	
MAIN_TEXTS	T801	Congestion!	Warning of network congestion	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T801b	Congestion!	Warning of network congestion	DBC43x	DBC43x	1	8 Reg.	25	128	
	T801c	Congestion!	Warning of network congestion	DBC444	DBC444	1	14 Bold, Cond.	25	208	
MAIN_TEXTS	T802	SOS call failed!	Indication of the failure of SOS call.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T802b	SOS call failed!	Indication of the failure of SOS call.	DBC43x	DBC43x	1	8 Reg.	25	128	
	T802c	SOS call failed!	Indication of the failure of SOS call.	DBC444	DBC444	1	14 Bold, Cond.	25	208	
MAIN_TEXTS	T803	Vacant number!	Indication of vacant number	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T803b	Vacant number!	Indication of vacant number	DBC43x	DBC43x	1	8 Reg.	25	128	
	T803c	Vacant number!	Indication of vacant number	DBC444	DBC444	1	14 Bold, Cond.	25	208	

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
MAIN_TEXTS	T804	Not reachable!	Indication of a not reachable number dialed.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T804b	Not reachable!	Indication of a not reachable number dialed.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T804c	Not reachable!	Indication of a not reachable number dialed.	DBC444	DBC444	1	14 Bold, Cond.	25	208	
MAIN_TEXTS	T805	Failed!	Indication of failure.	DBC446	DBC446	1	18 Reg.	25	261	
MAIN_TEXTS	T805b	Failed!	Indication of failure.	DBC43x	DBC43x	1	8 Reg.	25	128	
MAIN_TEXTS	T805c	Failed!	Indication of failure.	DBC444	DBC444	1	14 Bold, Cond.	25	208	
WEBB_TEXTS										
WEBB_TEXTS	K001	Internet	Is not translated by Mitel.		DBC446	1	18 Reg.	40	468	TRUE
WEBB_TEXTS	K002	Enter Address	Is not translated by Mitel.		DBC446	1	14 bold	40	180	TRUE
WEBB_TEXTS	K003	Delete	Is not translated by Mitel.		DBC446	1	14 bold	20	63	TRUE
WEBB_TEXTS	K004	Undo	Is not translated by Mitel.		DBC446	1	14 bold	20	63	TRUE
WEBB_TEXTS	K005	Bookmarks	Is not translated by Mitel.		DBC446	1	18 Reg.	40	430	TRUE
WEBB_TEXTS	K006	Disconnect?	Is not translated by Mitel.		DBC446	1	14 bold	25	218	TRUE
WEBB_TEXTS	K007	Yes	Is not translated by Mitel.		DBC446	1	14 bold	20	97	TRUE
WEBB_TEXTS	K008	No	Is not translated by Mitel.		DBC446	1	14 bold	20	97	TRUE
WEBB_TEXTS	K009	Saving Link	Is not translated by Mitel.		DBC446	1	14 bold	25	200	TRUE
WEBB_TEXTS	K010	Link exist	Is not translated by Mitel.		DBC446	1	14 bold	25	200	TRUE
WEBB_TEXTS	K020	General Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K021	Memory Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K022	The page cannot be displayed\n\nCannot find server or	Is not translated by Mitel.		DBC446	2	14 bold	80	438/line	TRUE
WEBB_TEXTS	K023	TCP/IP Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K024	SSL Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K025	Timeout Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K026	Cache Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K027	Authentication Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K300	Multiple Choices	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K301	Moved Permanently	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K302	Moved Temporarily	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K303	See Other	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
WEBB_TEXTS	K304	Not Modified	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K305	Use Proxy	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K307	Temporary Redirect	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K400	Bad Request	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K401	Unauthorized	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K402	Payment Required	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K403	Forbidden	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K404	Not Found	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K405	Method Not Allowed	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K406	Not Acceptable	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K407	Proxy Authentication Required	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K408	Request Timeout	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K409	Conflict	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K410	Gone	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K411	Length Required	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K412	Precondition Failed	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K413	Request Entity Too Large	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K414	Request-URI Too Long	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K415	Unsupported Media Type	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K416	Requested Range Not Satisfiable	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K417	Expectation Failed	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K500	Internal Server Error	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K501	Not Implemented	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K502	Bad Gateway	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K503	Service Unavailable	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K504	Gateway Timeout	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
WEBB_TEXTS	K505	HTTP Version Not Supported	Is not translated by Mitel.		DBC446	1	14 bold	40	438	TRUE
INPUT_LANGUAGE										

string type	string ID	default value	use	pixel check	language file	display rows	font size	max. length	max. pixel length	not to be translated
INPUT_LANGUAGE	A027	Greek	Greek.	DBC446	DBC446	1	14 Reg.	30	400	
INPUT_LANGUAGE	A027b	Greek	Greek.	DBC43x	DBC43x	1	8 Reg	25	120	
INPUT_LANGUAGE	A027c	Greek	Greek.	DBC444	DBC444	1	16 Bold	30	275	
INPUT_LANGUAGE	A028	Cyrillic	Cyrillic.	DBC446	DBC446	1	14 Reg.	30	400	
INPUT_LANGUAGE	A028b	Cyrillic	Cyrillic.	DBC43x	DBC43x	1	8 Reg	25	120	
INPUT_LANGUAGE	A028c	Cyrillic	Cyrillic.	DBC444	DBC444	1	16 Bold	30	275	